

AIX 5L Version 5.2



# Release Notes



AIX 5L Version 5.2



# Release Notes

**Note**

Before using this information and the product it supports, read the information in Appendix B, "Notices," on page 47.

**Eighth Edition (August 2005)**

**© Copyright International Business Machines Corporation 2002, 2004. All rights reserved.**

US Government Users Restricted Rights – Use, duplication or disclosure restricted by GSA ADP Schedule Contract with IBM Corp.

---

# Contents

<b>Chapter 1. Read This Before Installation</b> . . . . .	1
Required Hardware . . . . .	1
IBM eServer POWER4 pSeries Machines . . . . .	1
Some AIX Systems May Not Boot From CD-ROM . . . . .	2
Where to Find AIX 5L Version 5.2 Documentation . . . . .	2
Information Center . . . . .	2
Migration . . . . .	3
Minimum Memory and Disk Requirements . . . . .	3
Migration from AIX 4.2.1 . . . . .	3
xIC.rte Fileset . . . . .	3
Trusted Computing Base (TCB). . . . .	3
bos.clvm.enh Fileset after Migration to AIX 5L Version 5.2 . . . . .	3
sysck Errors on X11.loc.nl_BE.Dt.rte . . . . .	3
xmodmap/Zh_CN Errors after Migration . . . . .	3
KDE Desktop . . . . .	4
Performance Monitoring API . . . . .	4
SNMPv3 . . . . .	4
Kerberos . . . . .	4
AIX Toolbox for Linux Application Migration Information . . . . .	5
Multipath I/O (MPIO). . . . .	5
System V Printing Subsystem . . . . .	7
Installation . . . . .	7
Installing AIX 5L Version 5.2 . . . . .	7
Software License Agreements (SLA) . . . . .	8
Base Operating System Installation Options . . . . .	8
Memory Requirements . . . . .	9
Paging Space Requirements . . . . .	9
Disk Space Requirements . . . . .	9
Fixes for Installing the RH021019 Level of the pSeries 670 or pSeries 690 Firmware . . . . .	10
Other Installation Information . . . . .	10
Emergency Fix Management . . . . .	15
Service . . . . .	15
Service Update Management Assistant (SUMA) . . . . .	15
Fixes and Problem-Solving Databases. . . . .	16
<b>Chapter 2. AIX 5L Version 5.2</b> . . . . .	17
Base Operating System (BOS) . . . . .	17
64-bit System Identifier . . . . .	17
64-bit Kernel . . . . .	17
JFS2 File System Freeze and Thaw Feature . . . . .	18
Enabling and Disabling DMAPAPI on a JFS2 File System. . . . .	19
DMAPI and System or Volume Group Backup and Restore . . . . .	19
Korn Shell Compatibility . . . . .	19
Known Problems with ksh and ksh93 Commands. . . . .	19
JFS2 Log Attribute is Listed under JFS in the chfs Command . . . . .	19
New Flag for the mklv Command. . . . .	20
The -V Flag for the sar Command not Supported . . . . .	20
Perl . . . . .	20
C99 Language Interfaces . . . . .	21
IBM 32-bit SDK for AIX, Java 2 Technology Edition, Version 1.4 . . . . .	21
AIX Web Browser Transition to Mozilla . . . . .	21
License Use Management (LUM) Commands . . . . .	23
New PRIVSEG_LOADS Option for LDR_CNTRL Tunable Parameter . . . . .	23

Communications, Networking, and I/O . . . . .	23
7135 RAIDiant Array for AIX Requirements after Installing AIX 5L Version 5.2 . . . . .	23
Enable Link Polling and Time Interval for Link Polling Configuration Attributes . . . . .	23
Enhanced Error Handling (EEH) . . . . .	24
EtherChannel . . . . .	25
Gigabit Ethernet-SX PCI Adapter and IBM 10/100/1000 Base-T Ethernet PCI Adapter . . . . .	25
Gigabit Ethernet Fast Port Failover . . . . .	25
IPX/SPX Protocol Support . . . . .	26
Removal of Support for Devices . . . . .	26
The devices.artic960.5.2 Fileset . . . . .	26
The devices.pci.14108c00 Fileset . . . . .	27
Missing Resource Processing . . . . .	27
IBM Directory (LDAP) . . . . .	27
Dynamic Tracking and Fast I/O Failure of Fibre Channel Devices . . . . .	28
Internet Protocol (IP) over Fibre Channel . . . . .	28
Switch Network Interface (SNI) . . . . .	29
AIX iSCSI Software Initiator . . . . .	29
System Management . . . . .	30
Cluster Systems Management (CSM) . . . . .	30
CD and DVD Automount Facility . . . . .	31
SVR4 Printing . . . . .	31
Using the mkprtdap Command with IBM Directory 5.1 . . . . .	32
Parallel Printer Cable Selection . . . . .	32
Web-based System Manager . . . . .	32
Inventory Scout, Version 2.2.0.0 . . . . .	34
Tivoli Management Agent (TMA), Version 3.7.1.0 . . . . .	36
Other Software . . . . .	36
Compilers . . . . .	36
AIXlink/X.25 . . . . .	37
AIX Fast Connect, Version 3.1.2 . . . . .	37
Communications Server . . . . .	37
DCE for AIX . . . . .	37
<b>Chapter 3. Installing and Configuring a Secure System . . . . .</b>	<b>39</b>
Controlled Access Protection Profile and Evaluation Assurance Level 4+ (CAPP/EAL4+) . . . . .	39
CAPP/EAL4+ Compliant System Overview . . . . .	39
System Configuration for a CAPP/EAL4+ System. . . . .	42
Auditing . . . . .	43
Event Selection . . . . .	43
Setting Up Auditing . . . . .	43
<b>Appendix A. AIX 5L Version 5.2 Unsupported Items. . . . .</b>	<b>45</b>
AIX 5L Version 5.2 Unsupported Devices and Machines . . . . .	45
AIX 5L Version 5.2 Unsupported Functions and Filesets . . . . .	46
<b>Appendix B. Notices . . . . .</b>	<b>47</b>
Trademarks . . . . .	48

---

## Chapter 1. Read This Before Installation

**Note:** This software may contain errors that could result in critical business impact. It is highly recommended that you install the latest available fixes prior to using this software. Fixes can be obtained from IBM® eServer™ pSeries® Support at the following Web site:

<http://www.ibm.com/servers/eserver/support/pseries/aixfixes.html>

The AIX 5L™ Version 5.2 Release Notes include information that helps you install AIX 5L Version 5.2. These Release Notes support AIX 5L Version 5.2 with the 5200-06 Recommended Maintenance package. To view the most current version of the Release Notes, go to the online Release Notes in the IBM eServer pSeries Information Center. The Information Center is located at the following Web site:

<http://publib16.boulder.ibm.com/pseries/index.htm>

---

### Required Hardware

Only Common Hardware Reference Platform (CHRP) machines are supported.

To see if you have a CHRP machine, log into the machine as the root user, and run the following command:

```
bootinfo -p
```

To find out more about supported and unsupported items, see Appendix A, “AIX 5L Version 5.2 Unsupported Items,” on page 45.

### IBM eServer POWER4™ pSeries Machines

#### Required Levels of Hardware Management Console (HMC) and Firmware

The following items are required for using AIX 5L Version 5.2:

- Platform firmware version 3 or later.

To determine your platform firmware level, at the command prompt, type:

```
lscfg -vp | grep -p Platform
```

The last six digits of the ROM level represent the platform firmware date in the format, *YYMMDD*.

Firmware with dates between 020413 and 021024 or that has firmware level 2xYYMMDD is considered Version 2.

Firmware with dates between 021025 and 030324 or that has firmware level 3xYYMMDD is considered Version 3.

- You must have installed AIX 5L Version 5.2 with the 5200-01 Recommended Maintenance package or later, and upgraded to the latest Version 3 firmware service pack, and HMC Release 3 Version 2.0 or later.

For more information, see the following:

- HMC: See the *IBM Hardware Management Console for pSeries Installation and Operations Guide* in the Information Center.
- Platform Firmware: Contact your customer service representative.
- AIX®: See the *AIX 5L Version 5.2 Installation Guide and Reference* in the Information Center.

### Known Limitations for POWER4 Systems

#### Adapters

In Full System Partition mode, only one graphics adapter and USB adapter with one keyboard and

mouse are allowed per system. Only one graphics adapter and USB adapter with one keyboard and mouse are allowed per logical partition, and a maximum of eight logical partitions that have a graphics adapter and USB adapter are allowed.

### CPU Gard

Disable the CPU Gard functions if AIX 5L Version 5.2 and platform firmware levels older than October 2002 are used together by typing the following command:

```
chdev -l sys0 -a cpuguard='disable'
```

If platform firmware levels are upgraded, CPU Gard functions can be re-enabled by typing the following command:

```
chdev -l sys0 -a cpuguard='enable'
```

In either case, no system reboot is required for the changes to take effect.

### pSeries 690 Memory

The pSeries 690 model 681 (7040-681) supports a maximum system memory size of 1 TB (terabyte) with appropriate memory Feature Codes installed.

AIX 5.2 and Linux logical partitions can have nearly 512 GB logical partition memory sizes (about 503 GB after page table, hypervisor, and TCE table usage). AIX 5.2 and Linux logical partitions should have the **Small Real Mode Address Region** option selected on the HMC partition profile memory panel, and must be defined for greater than 256 GB logical partitions.

## Some AIX Systems May Not Boot From CD-ROM

Some AIX systems may not boot from CD-ROM because of firmware issues. To determine if your system will be affected by this problem, perform the following steps before you migrate or install a running AIX 4.3, AIX 5.1, or AIX 5.2 system:

1. At the command prompt, type the following:

```
lscfg -v1 cd*
```

2. Examine the data that is returned.

If *Part Number* is 04N2964 and *ROS Level and ID* is less than or equal to 1\_04 (for example, 1\_02, 1\_01, or 1\_00), contact your local service representative. Tell your service representative that your system requires the CD-ROM firmware upgrade that is described in RETAIN<sup>®</sup> TIP H1332.

If the data returned does not match the data described in the preceding paragraph, your system is not affected by this problem.

---

## Where to Find AIX 5L Version 5.2 Documentation

### Information Center

The IBM eServer pSeries Information Center is an information portal for AIX and pSeries customers. From this site, you can access the following:

- AIX Version 4.3, AIX 5L Version 5.1 for POWER, and AIX 5L Version 5.2 documentation
- Hardware documentation
- Message database for 7-digit error codes, LEDs, and error identifiers
- How-to's for users and system administrators
- FAQs
- Links to Redbooks<sup>™</sup>, white papers, and related products

To access the Information Center, go to the following Web site:

<http://publib16.boulder.ibm.com/pseries/index.htm>



---

## Migration

### Minimum Memory and Disk Requirements

The minimum memory required for AIX 5L Version 5.2 is 128 MB, and the minimum disk required is a 2.2 GB hard drive.

### Migration from AIX 4.2.1

A system running AIX 4.2.1 must be updated with the September 1999 or later Update CD before migrating to AIX 5.2. The CD label should have the number LCD4-0252-13 or higher. To check a running system, verify that the **bos.rte.install** file is at level 4.2.1.17 or higher.

### xlc.rte Fileset

If you are migrating to AIX 5.2 from AIX 4.2.x or AIX 4.3.x, check the level of the **xlc.rte** fileset by typing the following command:

```
lslpp -L xlc.rte
```

If the **xlc.rte** level is earlier than 5.0.2.x, you must apply APAR IY17981 before migrating to AIX 5.2. Without APAR IY17981 installed, the migrated system might fail to boot.

APAR IY17981 is available from the following Web site:

<http://www.ibm.com/servers/eserver/support/pseries/aixfixes.html>

## Trusted Computing Base (TCB)

### Known Problems and Workarounds

**The /dev/dlqllc file:** If you are on a migrated system with TCB enabled and you have the following error from the `tcback -n tree`:

```
3001-020 The file /dev/dlqllc was not found
```

Run the following command to re-create the **/dev/dlqllc** device:

```
# mkdev -c dlc -s dlc -t x25_qllc
```

### bos.clvm.enh Fileset after Migration to AIX 5L Version 5.2

The **bos.clvm.enh** fileset is not installed when your system is migrating to AIX 5.2. After the migration is complete, users of the **bos.clvm.enh** fileset will need to re-install the fileset from the AIX 5.2 installation media.

### sysck Errors on X11.loc.nl\_BE.Dt.rte

Users of the `nl_BE` language fileset might experience **sysck** error messages during migration to AIX 5.2. If this error is encountered, perform a force installation of the **X11.loc.nl\_BE.Dt.rte** fileset.

### xmodmap/Zh\_CN Errors after Migration

After you migrate to AIX 5.2, an **lppchk -f** command might give the following warning message:

```
lppchk: 0504-206 File /usr/lpp/X11/defaults/xmodmap/Zh_CN/keyboard could not be located.  
lppchk: 0504-206 File /usr/lpp/X11/defaults/xmodmap/Zh_CN could not be located.
```

If you have this condition, reinstall the **X11.loc.Zh\_CN.base.rte** fileset after migration.

## KDE Desktop

If the CDE and KDE desktops are both installed on a system migrated from AIX 4.3 to AIX 5.2 or on a system installed with AIX 5.2, the KDE desktop might not start from the CDE login. To fix this problem, remove the following CDE startup information from the `/etc/inittab` file:

**Note:** You must have root user authority to remove this CDE startup information.

```
dt:2:wait:/etc/rc.dt
```

Do not delete the following KDE entry from the `/etc/inittab` file:

```
kdm:2:once:/opt/freeware/kde/bin/kdm
```

## Performance Monitoring API

The Performance Monitoring API is contained in the **bos.pmapi** fileset. A beta version of the same code was made available to selected customers, and also through alphaWorks, under the name *pmtoolkit*.

The **bos.pmapi** fileset does not support the RS64-I (A35) processor. If you try to install the fileset on a machine with this processor, the installation fails and returns the following error:

```
setup_branchtable: Processor not yet supported.  
instal: Failed while executing the ./bos.pmapi.pmsvcs.post_i script.
```

When you are migrating from any level of AIX with any level of the beta fileset installed, you must uninstall the **pmtoolkit** fileset and reboot the machine before you install the **bos.pmapi** fileset. If you do not do this, the machine will fail to boot when you attempt to load the **pmtoolkit** fileset's kernel extension.

Verify that the **pmtoolkit** fileset is installed by typing the following at the command line:

```
ls1pp -l pmtoolkit
```

- If you get the following output:

```
ls1pp: 0504-132 Fileset pmtoolkit not installed
```

you can safely install the **bos.pmapi** fileset.

- If you get the following output:

Fileset	Level	State	Description
-----			
Path: /usr/lib/objrepos			
pmtoolkit	1.3.1.6	COMMITTED	Performance Monitor Toolkit 1.3.1

complete the following steps:

1. Run the following command:

```
installp -u pmtoolkit
```

2. Reboot the machine. After the machine reboots, you can safely install the **bos.pmapi** fileset.

## SNMPv3

After you migrate to AIX 5.2, the non-encrypted version of SNMPv3 will run by default. If you had your own community, trap, or smux entries in your `/etc/snmpd.conf` file, those must be manually migrated to the `/etc/snmpdv3.conf` file. For instructions on how to migrate this information, see "Network Management" in *AIX 5L Version 5.2 System Management Guide: Communications and Networks*.

## Kerberos

All the secure remote commands use the Kerberos Version 5 library and the GSSAPI library provided by IBM Network Authentication Service Version 1.3 or later that is located on the *AIX 5L Version 5.2 Expansion Pack* CD. However, you must install the **krb5.client.rte** fileset.

If you are migrating to AIX 5.2 and had Kerberos Version 5 or Kerberos Version 4 installed, the installation scripts will prompt you to install the **krb5.client.rte** fileset. The secure remote commands support Kerberos clients and servers from both Native Kerberos 5 and DCE.

For more information, see "Understanding the Secure Rcmds" in the *AIX 5L Version 5.2 System User's Guide: Communications and Networks*.

## AIX Toolbox for Linux Application Migration Information

If you previously installed the AIX Toolbox for Linux Applications and the level of the **rpm.rte** fileset is lower than 3.0.5.20, remove that software from the system before migrating to AIX 5.2. The Toolbox software installed with **rpm.rte** levels prior to 3.0.5.20 are incompatible with software from the AIX Toolbox installed on AIX 5L Version 5.2 because of shared library restructuring.

Remove the software if you are performing a preservation installation and you established an **/opt/freeware** file system for the Toolbox software. The files in that file system will not be automatically overwritten during a preservation installation. To remove your existing rpm filesets, use the **destroyRPMS** tool available in the **/contrib** directory on the *AIX Toolbox for Linux Applications* CD by typing the following:

```
mount -vcdvfs -oro /dev/cd0 /mnt  
/mnt/contrib/destroyRPMS
```

If you are migrating your system from AIX 4.3.3 to AIX 5L and you installed **rpm.rte** without creating your own **/opt** or **/opt/freeware** file system, after running the **destroyRPMS** command, it is recommended that you remove the **/opt/freeware** and **/usr/opt/freeware** directories prior to migrating. On AIX 5L, the system provides a **/opt** file system into which **rpm.rte** is normally installed. However, if rpm finds a preexisting **/usr/opt/freeware** directory, it will use this location instead. You don't need to do this if you want your rpm freeware installed under the **/usr** file system, but the **/opt** file system is recommended.

If you have already migrated with the **/usr/opt/freeware** file system and wish to change this afterwards, run the **destroyRPMS** command again, remove any existing **/usr/opt/freeware** and **/opt/freeware** directories, and install **rpm.rte** again.

Additional information is also available on the *AIX Toolbox for Linux Applications* CD in the **/README.TXT** file.

## Multipath I/O (MPIO)

After you upgrade to AIX 5L Version 5.2 with the 5200-01 Recommended Maintenance package or later, some disk devices will no longer be configured as *other FC disk*. These devices instead will be configured as *MPIO other FC disk*. The affected devices are EMC SYMMETRIX, HDS OPEN, and IBM TotalStorage® disk subsystems. These devices are configured as an MPIO device if the device was previously configured as *other FC disk*.

The following describes some of the similarities and differences that will be seen after the device has migrated to an *MPIO other FC disk*.

### Terminology:

- A path is each physical connection between the host system and the device.
- A path control module (PCM) is a device specific module that manages a device's I/O across its paths.

A device configured as *other FC disk* has the following properties:

- Contains multiple device instances created for each path the device was detected on.
- Supports user-changeable device attributes.
- Can migrate to a vendor-specific device when vendor-supplied, device-specific ODM pre-definitions are installed.

- Is meant to be a transitory state during boot and install. The vendor-specific device ODM predefines should be installed before using the device in a production environment.

A device configured as *MPIO other FC disk* has the following properties:

- Contains only one device instance created and multiple path instances created. Also contains one path instance for each physical connection between the host system and the device.
- Supports user-changeable device attributes. There may be additional attributes that are PCM specific.
- Can migrate to a vendor-specific device when vendor-supplied, device-specific ODM pre-definitions are installed.
- Presently is not supported by PowerPath, MDS, or SSD path management products. To support any of these products the vendor-specific no-MPIO ODM pre-definitions must be installed. Attempting to control a device configured as an MPIO device will produce undetermined results. Data integrity issues will exist if the device is operated in this configuration.
- Is supported in a production environment. Device-specific vendor ODM pre-definitions are not required to be installed before using in a production environment.
- Allows for installing and booting to an MPIO device.

## Migration Issues

The following describes migration issues if the *MPIO other FC disk* support is removed after devices have been configured as *MPIO other FC disk*:

Migrating to an *other FC disk* can occur if the *MPIO other FC* support is removed. In this case, where the update is uninstalled with the force option, the AIX 5.2 release of MPIO will handle the migration. If the system is rebooted, the device instance will be in the define state. During migration, the device instance will be left in the define state and a new *other FC disk* instance will be created.

If the system is not rebooted and the device instance is in the define state, the device instance will be left in the define state and a new *other FC disk* instance will be created.

If the system is not rebooted and the device instance is in the available state, the device instance will be left unchanged.

There may also be *other FC device* instances created. If the *MPIO other FC device* is not open, there will be an *other FC device* instance created for each path the device is detected on. If the *MPIO other FC device* is in the open state, there will not be any *other FC device* instances created. This is because the *MPIO other FC device* will have already issued a **SCIOSTART** command to the FC adapter for each of the paths. The FC adapter will not allow two devices with the same worldwide name and worldwide nodename to exist in its internal data structures.

If *other FC device* instances were created, sending I/O to the device while it is configured as both *MPIO other FC* and *other FC device* may cause indeterminate device behavior or data damage. Reboot the system to correct this condition. After the system is rebooted, the *MPIO other FC device* instance will be in the defined state and can be removed using the **odmdelete** command. The **rmdev** command will not remove the device due to the missing pre-definitions.

See “MPIO Features” for information about additional features of MPIO devices.

## MPIO Features

Support for parallel SCSI SCSD disks was released in AIX 5L Version 5.2, and support for MPIO Fibre Channel disks is implemented in AIX 5L Version 5.2 with the 5200-01 Recommended Maintenance package. Some devices will configure differently than in previous releases. See “Multipath I/O (MPIO)” on page 5 for additional information.

The following describes the major features added to the MPIO device capabilities:

- Tracing the SCSI and Fibre Channel device drivers now includes traces within the MPIO FRAMEWORK. The MPIO FRAMEWORK is the interface layer between the AIX device driver and the path control module. The path control module (PCM) determines which path should be used to send I/O from the device driver to the target device.
- AIX PCM supports tracing within its interface routines. The trace hook for PCMs is 0x17B00000 HKWD\_PCMKE. Vendor supplied PCMs can also use this trace hook.
- Dump support for MPIO FRAMEWORK and AIX PCM data structures are included in the component dump table (CDT). If a system crashes the MPIO FRAMEWORK and AIX PCM data structures are included in the dump and can be viewed using the **kdb** command.
- AIX PCM health-checking can test device connections (paths). This capability can re-enable failed paths. In the previous release of MPIO, you were required to run the **chpath** command to re-enable failed paths.

Additional information about MPIO is available in the following AIX publications:

*AIX 5L Version 5.2 System Management Concepts: Operating System and Devices* in the section titled *Multipath I/O*.

*AIX 5L Version 5.2 System Management Guide: Operating System and Devices* in the section titled *MPIO Devices*.

## System V Printing Subsystem

The System V Printing Subsystem is an alternate printing subsystem in AIX. The installation of the **bos.svprint.\*** filesets in a TCB environment requires that the **lp** user ID (UID:11) and **lp** group ID (GID:11) be present in the system. Otherwise the installation of these filesets will fail.

To avoid this problem, create the **lp** user (UID:11) and **lp** group (GID:11) accounts on the AIX 4.3.3 system prior to the migration.

---

## Installation

This section contains information about installing AIX 5.2 that supplements the information contained in the AIX 5.2 installation documentation.

The following publications describe AIX 5.2 installation:

- *AIX 5L Version 5.2 Operating System Installation: Getting Started*
- *AIX 5L Version 5.2 Installation Guide and Reference*

Both installation guides are available online in the pSeries Information Center in the AIX 5L Version 5.2 documentation category and in printed hardcopy.

To order these installation guides, contact your point of sale, or in the U.S., call IBM Customer Publication Support at 1-800-879-2755. Give the order number of the book you want to order.

To obtain AIX 5L Version 5.3 installation hints and tips, visit the Subscription Service at the following Web site:

<https://techsupport.services.ibm.com/server/pseries.subscriptionSvc>

## Installing AIX 5L Version 5.2

The following methods can be used to install AIX 5L Version 5.2:

- Complete overwrite installation
- Preservation installation
- Migration installation

**Note:** After you install or migrate a system to AIX 5L Version 5.2, you can install a lower level of AIX by restoring a system backup or by performing a new and complete overwrite with base media. Preservation installations from AIX 5L Version 5.2 to a lower level of AIX are not supported.

If your system has AIX 5.2 with 5200-00, AIX 5.2 with 5200-01, AIX 5.2 with 5200-02, AIX 5.2 with 5200-03, or AIX 5.2 with 5200-04 installed (you can verify the level by running the **oslevel -r** command), then you can use the base media to update to AIX 5.2 with 5200-05, or you can use the Update CD. In either case, use the **smitty update\_all** command to perform the update. Because only the base install images are on the media, if you use the product media to update to AIX 5.2 with 5200-05, you cannot reject the software and return to the previous level.

To install AIX 5L Version 5.2, boot your system from the product media, and follow the instructions in the *AIX 5L Version 5.2 Installation Guide and Reference*.

**Note:** AIX 5L Version 5.2 cannot be installed on MCA (Micro Channel<sup>®</sup> Architecture) or PowerPC Reference Platform<sup>®</sup> (PReP) machines.

For more information about migration, see “Migration” on page 3.

## Software License Agreements (SLA)

When you are using ASCII displays, there are some instances where the Software License Agreements may not be fully displayed. In this event, the License Agreements can be viewed in all languages at the following Web site:

<http://www.ibm.com/software/sla/slabdb.nsf>

## Base Operating System Installation Options

The information in this section supplements the “Installation Options” chapter of the *AIX 5L Version 5.2 Installation Guide and Reference*.

In the Base Operating System installation menus, if there are more than 50 disks on the system, the disks are ordinarily grouped by adapter. However, for some types of disks, the grouping is slightly different:

### SCSI disks

Disks may be grouped by adapter or SCSI bus

### IBM TotalStorage DS4000

Disks are grouped by disk array controller (DAC)

In each case, the user can select the adapter, SCSI bus, or DAC by name and see the associated disks. The physical location of the adapter, SCSI bus, or DAC is also displayed.

## Graphics Software Bundle Requires Two CDs

Due to space constraints on the AIX base product media CDs, the graphics software bundle is now included on the *Volume 2* CD. For installations using CD media, you are prompted for the *Volume 2* CD if you install with the defaults for an overwrite or preservation installation (Graphics Software = yes).

If you create a Network Installation Management (NIM) `lpp_source`, you will not be prompted for the *Volume 2* CD to add the graphics software to the `lpp_source`. To add the graphics software after creating the `lpp_source`:

1. Type the **smitty nim\_update\_add** command.  
The **Add Software to an lpp\_source** menu is displayed.
2. Select the **Graphics** bundle for **INSTALLP BUNDLE containing packages to add**.



The contents of the graphics bundle was changed with AIX 5L with 5200-03. The bundle now includes the **bos.docsearch** and the **bos.docregister** software required by the **sysmgt.websm** fileset. This additional software is still on the *Volume 1* CD, and you are prompted for this additional software.

## Graphics Software Support and Desktop Choices

The Desktop choices are CDE, KDE, GNOME, and NONE. If you select NONE, a minimal configuration is installed, including:

- X11
- Java™
- Web-based System Manager
- Document Search and Document Registry software

For new and complete overwrite installations, the graphics bundle installation always defaults to yes (Graphics Software = yes), which is to install graphics software support, whether or not the console is graphical. This allows for remote access to the applications from other graphical systems.

The Desktop installation option is not available if the console is non-graphical.

## Memory Requirements

AIX 5L Version 5.2 requires a minimum of 128 MB of physical memory.

## Paging Space Requirements

AIX 5L Version 5.2 creates a 512 MB paging space (*/dev/hd6*) for all new and complete overwrite installations.

## Disk Space Requirements

AIX 5L Version 5.2 requires a minimum of 2.2 GB of physical disk space for the same set of installed filesets due to increased library sizes and additional function.

**Note:** The following measurements provide information about disk usage when you install AIX 5L Version 5.2 as compared to previous versions.

*Base AIX Installation (Graphical System with CDE-Default)*

Location	AIX 4.3.3 Allocated (Used)	AIX 5L for POWER Version 5.1 Allocated (Used)	AIX 5L Version 5.2 with the 5200-05 Recommended Maintenance package Allocated (Used)
/	4 MB (2.5 MB)	8 MB (5.6 MB)	16 MB (9 MB)
/usr	294 MB (279 MB)	385 MB (370 MB)	928 MB (919 MB)
/var	4 MB (1.3 MB)	4 MB (1.4 MB)	16 MB (5 MB)
/tmp	16 MB (0.6 MB)	20 MB (0.9 MB) see note	24 MB (0.8 MB)
/opt	N/A	4 MB (0.2 MB)	24 MB (9 MB)

**Note:** If the */tmp* directory is less than 32 MB, it is increased to 32 MB during a migration installation so that the AIX 5L Version 5.2 boot image is successfully created at the end of the migration.

During a migration installation, if */opt* exists only as a directory and has less than 3 MB of data, then a new */dev/hd10opt* logical volume and */opt* file system are created, and the data that existed in the */opt* directory is moved to the new */opt* file system.

If there is more than 3 MB of data in the `/opt` directory, then the new logical volume and file system are not created.

If any existing file system has a mount point in the `/opt` directory, or a mount point of `/opt` itself, the new logical volume and file system are not created.

## Fixes for Installing the RH021019 Level of the pSeries 670 or pSeries 690 Firmware

The following fixes are recommended prior to installing the RH021019 level of the pSeries 670 or 690 (7040-671 or 7040-681) firmware:

- HMC version update: Update the HMC to the latest level listed at the following HMC Web site:  
<http://techsupport.services.ibm.com/server/hmc>
- AIX 5L Version 5.2 APAR: Update your images with APAR IY34493, which is available at the following Web site:  
<http://www.ibm.com/servers/eserver/support/pseries/aixfixes.html>

An AIX fix to the **csmlclient** fix is recommended for DLPAR operations and the Service Focal Point operation. The APAR number for the **csmlclient** fix is IY34493.

The **csmlclient** fix addresses a problem where a configuration daemon relating to the HMC function used in DLPAR operations and Service Focal Point operation eventually stops, preventing future DLPAR operations and Service Focal Point operations.

## Other Installation Information

### Installation Packaging Formats

AIX 5L Version 5.2 supports the following installation-packaging formats:

- `installp`, AIX system installation command and packaging format
- RPM, a Linux installation command and packaging format
- ISMP, InstallShield Multi-Platform packaging format

With the **geninstall** command, you can list and install packages from media that contains installation images packaged in any of the listed formats. The **geninstall** and **gencopy** commands recognize the non-`installp` installation formats and either call the appropriate installers or copy the images, respectively.

The AIX 5L Version 5.2 product media contains `installp` packages and RPM packages that are installed during a BOS installation. The `installp` packages are located in the following path, where *mount\_point* is the mount point:

```
mount_point/installp/ppc
```

The RPM packages are located in the following path, where *mount\_point* is the mount point:

```
mount_point/RPMS/ppc
```

If you have media that contains ISMP packages for AIX 5.2, the ISMP packages are located in the following path, where *mount\_point* is the mount point:

```
mount_point/ismppc
```

The **installp**, **bffcreate**, **geninstall**, **gencopy** and **nim** commands recognize this media structure.

For more information about software packaging, see the Software Product Packaging Concepts section in the *AIX 5L Version 5.2 Installation Guide and Reference*.



**Example:** If you are using the **bfcreate** command or a user interface to copy images from CD to a directory on the disk, new subdirectories will be created in the target directory and the images will be placed in those directories.

In AIX 4.3, the default target directory for the **bfcreate** command was the **/usr/sys/inst.images** directory.

In AIX 5.2, if the following command is used on a PowerPC® machine:

```
bfcreate -d /dev/cd0 all
```

the default target directory is the **/usr/sys/inst.images/installp/ppc** directory.

Use the **gencopy** command as follows:

```
gencopy -d /dev/cd0 all
```

In addition to all of the **installp** images, you also get the **rpm** images that are contained on the product media, as follows:

```
cd /usr/sys/inst.images/RPMS/ppc
find . -print
./cdrecord.aix4.3.ppc.rpm
./mkisofs.aix4.3.ppc.rpm
```

Due to this change, you might need to update any custom scripts in which image locations are hardcoded.

### **mkcd and New IDE DVD-RAM Drive (Support for System Backup and Volume Group Backup)**

A new slimline IDE DVD-RAM drive is now available (Feature Code 5751). This drive is not supported by the GNU or open source **cdrecord** and **readcd** commands. Therefore, to create system backups or volume group backups using the **mkcd** command, you must create the backups using the **-U** flag.

Note that Universal Disk Format (UDF)-formatted media is not supported prior to AIX 5.2. You can boot and install a UDF-formatted system backup, but you cannot mount the UDF backup or extract files on a running system that is at a level lower than AIX 5.2. To pass files between AIX 5.2 and AIX 5.1, use either another device or other commands, such as **tar**, **cpio**, or **backup**.

For more information about creating CD-R and DVD-RAM backups, see the **/usr/lpp/bos.sysmgmt/mkcd.README.txt** file.

To support booting from UDF backup media, older systems might require later firmware. For firmware updates, see the following Web site:

<http://techsupport.services.ibm.com/server/mdownload>

### **IBM 4.7 GB IDE Slimline DVD-RAM Drive Limitations**

The following limitations apply to the IBM 4.7 GB IDE Slimline DVD-RAM drive:

- The DVD-RAM drive writes only to 4.7 GB and 9.4 GB DVD-RAM media and reads from CD-ROM, CD-R, CD-RW, DVD-ROM, and DVD-RAM media. If you try to write to CD media, you are prompted to insert DVD-R media.
- ISO format is not supported.
- DVD video is not supported.
- Nonbootable mksysb backups fail. After you boot the system from the product media, the DVD-RAM does not mount to restore the mksysb backup.

### **BOS Installation Support for Fibre Channel Boot**

BOS installation supports installation to Fibre Channel-attached disks. Either bootable AIX 5L Version 5.2 installation media or NIM resources prepared from such media are required. The Fibre Channel-attached disks must be attached to a Fibre Channel host adapter that supports boot capability. However, Fibre

Channel drivers that have multiple, physical connections to the host or drivers that require supplemental device software should not be chosen as **rootvg** drives.

A Fibre Channel-attached disk can be identified by a World Wide Port Name and Logical Unit ID. To see the format of the World Wide Port Name and Logical Unit ID, type:

```
lsattr -E -0 -l DiskName
```

- In a non prompted BOS installation, you can specify a Fibre Channel-attached disk in the `target_disk_data` stanza of the **bosinst.data** file using the following as an example:

```
SAN_DISKID = (World Wide Port Name)/(Logical Unit ID)
```

In the above example, *(World Wide Port Name)* and *(Logical Unit ID)* are each in the format returned by the **lsattr** command, that is, "0x" followed by one to 16 hexadecimal digits.

- In a prompted BOS installation, the BOS menus display the list of available disks and associated information. You can select the desired disks.

## System Dump

The default system dump device is paging space. This default may not be adequate for system configurations that have large memory sizes or when system availability is a concern.

For large memory systems, AIX allocates a dedicated dump device, named **/dev/lg\_dumplv**, if disk space is available. The following table shows the sizes of the dump devices based on the amount of real memory present in the system.

*Dump Device Size (Based on System Real Memory)*

Real Memory	Dump Device
4 GB < 12 GB	1 GB
12 GB < 24 GB	2 GB
24 GB < 48 GB	3 GB
>= 48 GB	4 GB

**Note:** If the root user starts a dump to a **/dev/sysdumpnull** dump device, the system will crash and no dump will occur.

The dump is now copied to tape in **pax** format instead of **tar**, because **pax** supports large (greater than 2 GB) files.

The **dumpcheck** facility runs by default each day at 3:00 p.m. local time. See the root **crontab** file to change the time that the **dumpcheck** facility runs. The **dumpcheck** facility ensures that there is enough space in the dump device and copy directory to receive the system dump. If dump compression will facilitate a system dump, it will be enabled unless you have manually disabled it. The results of the **dumpcheck** facility are in the system error log.

## Network Installation Management

Network Installation Management (NIM) includes a readme file that is installed with the NIM Master **bos.sysmgt.nim.master** fileset. The path name of the file is **/usr/lpp/bos.sysmgt/nim/README**. The readme file contains additional information about the AIX 5L Version 5.2 NIM product and includes the following topics:

- Restrictions on SPOT Creation for Releases Prior to 5.2 (New LPP\_SOURCE Directory structure)
- Web-based System Manager NIM May Have Problems Installing SW on Client Machines
- Restrictions on Customize Operation for RPM Packages
- Steps Necessary For Adding GNOME -or- KDE Desktop Support

## The mksysb Tape

When you use the **mksysb** command to create a backup tape, apply the following APARs to the system before creating the backup tape:

- AIX 5.1 APAR IY54804
- AIX 5.2 APAR IY53546

For more information, see the `/usr/lpp/bos.sysmgmt/README` file.

If you want to boot a **mksysb** tape that has been created on a system that has the appropriate APAR installed, as described above, and the system is one of these models: 7040-681, 7038-6M2, 7028-6C4, 7039-651, or 7029-6C3, then you should install firmware version 3x040319 or later, where x designates the model (H, J, K, R, or F). Other models should use the real-base workaround.

**Real-base Workaround:** If your system fails to boot from a **mksysb** tape, you might have encountered a problem that can be identified and resolved with the following instructions:

**Note:** This procedure does not work on machine types 7028, 7029, 7038, and 7040 and should not be used. For information about how to boot these machine types from a **mksysb** tape, see “Alternate mksysb Solution.” Affected systems include all CHRP architecture systems, beginning with the F50 model.

1. Access the firmware command line prompt, which usually appears as an option in the SMS menus.
2. At the firmware command line prompt, type the following commands:

```
setenv real-base 1000000
reset-all
```

The system will reboot.

3. Boot the system from the tape, assuming that you have an otherwise valid boot image on your tape media.

**Alternate mksysb Solution:** This solution works on all systems, but requires AIX product media at the same release (or higher) as the **mksysb** tape. This is the only solution for machine types 7028, 7029, 7038 and 7040.

1. Boot your system from the AIX product media (CD or network boot).
2. When the installation menus appear, select **3 Access Advanced Maintenance Functions**, and then select **4 Install from a System Backup**.
3. Select **tape drive** and proceed to install.

*Recovering from Setting setenv real-base on Machine Types 7028, 7029, 7038 and 7040:* When the **setenv real-base** command has been run on machine types 7028, 7029, 7038, or 7040, the system will start to boot, some messages or data will display, then the system will stop on the open firmware prompt as shown below:

```
ok
0 >
```

To restore the correct setting, type the following command:

```
0 > delenv real-base
```

This command will delete the real-base variable. After the above command is run, the system must be power-cycled, and AIX will boot normally from the hard disk. This solution will keep all other NVRAM data, such as partition information, intact.

**The mksysb Command:** The method used by the **mksysb** command to restore data through system backups has changed.

Enhancements have been added to more fully restore customized data so that a system more closely resembles the system at the time the backup was performed. This occurs when restoring a backup on the system that the backup originated from. These enhancements were added to reduce the amount of additional work that sometimes needs to happen to restore devices to their customized configuration at the time of backup.

If devices were removed or replaced from the system after the backup was created, their information will be restored when you are installing a backup, and the system will show these devices in a defined state.

These enhancements do not affect installing the backup onto other systems, or *cloning*.

## Reliable Scalable Cluster Technology (RSCT)

The RSCT Resource Monitoring and Control (RMC) application is part of RSCT. The RSCT includes a readme file that is installed with the **rsct.core.utils** fileset. The file is located at **/usr/sbin/rsct/README/rsct.core.README**, and contains additional information about the RMC application.

**Restriction for Japanese Locales:** When the responses specified with the predefined **notifyevent** script are used in Japanese locales, alphanumeric (English) characters should be used for the condition name. If the condition name has non-alphanumeric characters in the mail header, it will be damaged. To work around this problem, you can modify the **notifyevent** script to not use the **\$ERRM\_COND\_NAME** environment variable in the mail subject.

**Service Resource Manager (ServiceRM):** Service Resource Manager (ServiceRM) is a Reliable, Scalable, Cluster Technology (RSCT) resource manager that creates serviceable events for problems found by AIX Diagnostics. ServiceRM sends these events to the Service Focal Point on the Hardware Management Console (HMC).

## Firmware Limitation

The firmware in many of the PCI bus-based RS/6000<sup>®</sup> machines is limited in regard to the region of the hard disk from which it can read a boot image. This problem will not be encountered under most circumstances. The symptom of the problem is a failure to boot from hard disk, resulting in a message from firmware similar to unrecognized Client Program format.

Affected machines can be identified most easily as the machines that provide access to the firmware System Management Services by pressing the F1 key on the system-attached keyboard or the 1 key on a TTY keyboard.

Firmware on the affected machines cannot read the boot image from the hard disk if any part of the boot image is located beyond the 4 GB boundary on the hard disk. This is not a problem for most customers because the AIX installation process creates the boot logical volume at the beginning of the disk. This is achieved by using the **-a** flag with the **mklv** command and specifying **e** (which corresponds to **edge**) as the parameter for the **-a** flag. Using the **mklv** command with this parameter results in the boot logical volume being created at the edge of the hard disk, and the resulting address that the firmware uses to read the boot image will be within a safe range. The AIX installation process has always created the boot logical volume near the edge of the hard disk because that region of the hard disk has the slowest access time, and this allows other regions of the hard disk to be used by file systems that can benefit from increased performance.

The only way that you can encounter this problem is by creating and initializing a new boot logical volume that extends past the 4 GB boundary of the hard disk.

In almost all cases, you do not need to create a new boot logical volume, but if you do, use the **lsvg** and **lslv** commands to verify that the newly created boot logical volume does not reside above the 4 GB address on the hard disk.

An example of this calculation follows:

1. Run **lsvg rootvg** to determine PP SIZE. On a 4.5 GB hard disk, the default PP SIZE is 8 MB. Make a note of that size.
2. Run **lslv -m bootlv00**, where *bootlv00* is the name of the newly created boot logical volume.

The numbers in the second, fourth, and sixth columns indicate the physical partitions that have been assigned to the boot logical volume. If the PP SIZE is 8 MB, the boot logical volume must not use any physical partition above 511 ( $512 * 8 = 4096$ , which is 4 GB). Similarly, if the PP SIZE is 16 MB, the boot image must not use any partition above 255, and if the PP SIZE is 4 MB, the boot image must not use any partition above 1023.

## Machine Limitations with Universal Disk Format (UDF)

When booting a 7043-150 or 7046-B50 system from the Universal Disk Format (UDF) media, use the **O/F** command instead of SMS. The following is an example of how to use the **O/F** command:

```
boot /pci@fef00000/scsi@4,0:1,\ppc\bootinfo.txt
```

## Emergency Fix Management

Emergency Fix (efix) Management provides utilities that package, install, and manage efixes, which involves the following commands:

**epkg** The efix packager

**emgr** The efix manager

The **epkg** command creates efix packages that can be installed by the **emgr** command. After the efix is installed, the **emgr** command can be used to list, check, remove, and perform other operations with the installed efixes.

---

## Service

### Service Update Management Assistant (SUMA)

This section includes information about the Service Update Management Assistant (SUMA).

#### Overview

Service Update Management Assistant (SUMA) brings patch download management to your server. SUMA mirrors the functionality of the Fix Central Web site from the command line or SMIT, eliminating the need for graphics support or a Web browser. In addition, SUMA includes integrated scheduling capabilities to enable repeating tasks and unattended downloads during periods of low network activity. SUMA is installed with the **bos.suma** fileset.

#### Requirements

SUMA requires the following, which are included automatically when you install the **bos.suma** fileset:

- The latest patch level of **perl.rte** (5.6.0.10 for AIX 5.1 or 5.8.0.10 for AIX 5.2)
- The **perl.libext** fileset (2.0.56.0 for AIX 5.1 or 2.0.58.0 for AIX 5.2)

SUMA also requires an active connection to the Internet. Proxies are supported. For more information, see the **suma** man page by typing `man suma`.

Secure queries and downloads are supported if OpenSSL is installed. OpenSSL is not installed by default, but it is available on the *Toolbox for Linux Applications CD*.

## Usage

SUMA activity is based on the concept of the Task. Multiple Tasks can be stored to perform separate functions. Configurable Task default settings are used to complete underlying options not explicitly overridden when invoking SUMA. Base configuration settings affect all operations. For more information, see the **suma** man page by typing `man suma`.

SUMA functionality is available from the command line with the **suma** command, which is located in the **/usr/suma/bin** directory, with a symbolic link in the **/usr/sbin** directory. The following are examples of command-line usage:

- To download APAR IY78954 immediately, type the following:  

```
suma -x -a RqType=APAR -a RqName=IY78954
```
- To search for PTF U578619 every night at 3:00 a.m. and then download it when it becomes available, type the following:  

```
suma -s "0 3 * * *" -a RqType=PTF -a RqName=U578619 -a Repeats=n
```
- To configure the default download location for newly created tasks, type the following:  

```
suma -D -a DLTarget=/export/lpp_source1
```
- To configure SUMA to use HTTPS and a proxy server for queries and downloads, type the following:  

```
suma -c -a HTTPS_PROXY=http://proxy.company.com:8143/ \
-a FIXSERVER_PROTOCOL=https -a DOWNLOAD_PROTOCOL=https
```

SUMA functionality is also available in SMIT using the `suma` fast path.

## Installation

You can use one of the following installation methods to install SUMA:

- The SMIT `install_software` fast path by typing the following:  

```
smitty install_software
```
- The **geninstall** command by typing the following:  

```
geninstall -d media I:bos.suma
```

where `-d` is the device or directory containing the images to install, and *media* is the type of media from which to install

## Fixes and Problem-Solving Databases

You can download AIX fixes from the following IBM eServer Support Web site:

<http://www.ibm.com/servers/eserver/support/pseries/aixfixes.html>

You can also search technical databases, including:

- APARS
- Tips for AIX administrators

---

## Chapter 2. AIX 5L Version 5.2

The following are some of the features that were introduced in AIX 5L Version 5.2:

- Dynamic Logical Partitioning (DLPAR)
- Capacity Upgrade on Demand (CUoD)
- Advanced RAS features
- Enhancements to Workload Manager
- Cluster Systems Management (CSM) for monitoring and administering multiple machines (both AIX and Linux) from a single point of control

To find out more about the new features introduced in AIX 5L Version 5.2, refer to the Information Center at the following Web site:

<http://publib16.boulder.ibm.com/pseries/index.htm>

---

### Base Operating System (BOS)

#### 64-bit System Identifier

AIX 5L Version 5.2 with the 5200-03 Recommended Maintenance package or later provides a 64-bit system identifier for compatibility with future systems. This identifier is available in the following forms:

##### **id\_to\_system**

The **id\_to\_system** identifier is unique for a system, but it is common to all partitions on the system. This identifier should be used by applications to license to a system. The value can be obtained using one of the following commands:

```
uname -F
lsattr -El sys0 -a id_to_system
```

##### **id\_to\_partition**

The **id\_to\_partition** identifier is similar to the **id\_to\_system** identifier, but it also includes the partition number and therefore is unique for each partition. This identifier should be used by applications to license to a partition. The value can be obtained using one of the following commands:

```
uname -f
lsattr -El sys0 -a id_to_partition
```

#### 64-bit Kernel

AIX 5L Version 5.2 provides a scalable 64-bit kernel that is capable of supporting large application workloads running on 64-bit hardware. The 64-bit kernel scalability is primarily provided through a larger kernel address space. This space supports larger system software applications without requiring practical bounds and kernel extension interfaces.

**Note:** The 32-bit kernel continues to be supported on AIX 5L Version 5.2. The maximum real memory supported by a 32-bit kernel system (or partition) is 96 GB.

#### System Support

For information about supported and unsupported items, see Appendix A, "AIX 5L Version 5.2 Unsupported Items," on page 45.

#### Base Functionality

The AIX 5L Version 5.2 kernels provide the same functionality, regardless of which kernel is being used. The 32-bit and 64-bit kernel systems have common base libraries, commands, utilities, and header files.

Differences between 32-bit and 64-bit kernel systems are limited to the following:



- **System and I/O Support.** The 64-bit kernel limits support to 64-bit POWER-based systems, while the 32-bit kernel supports both 32-bit and 64-bit POWER-based systems. In addition, the 64-bit kernel does not support all I/O that is supported by the 32-bit kernel.
- **Application Support.** The 64-bit kernel supports both 32-bit and 64-bit applications. Application source and binaries are portable between AIX 5L Version 5.2 64-bit and 32-bit kernel systems, in the absence of any application dependencies on internal kernel details or on kernel extensions that are not supported under the 64-bit kernel but are supported under the 32-bit kernel.
  - **Binary Compatibility.** Binary compatibility is provided for 32-bit applications running on earlier versions of AIX on POWER-based systems, except for applications linked statically or applications dependent on undocumented or unsupported interfaces. In addition, some system file formats have changed, and 32-bit applications processing these files might need to be recompiled.
  - **Application Scalability.** AIX 5L Version 5.2 provides a more scalable application binary interface (ABI) for 64-bit applications. To take advantage of the scalability improvements to 64-bit programs, all 64-bit applications and libraries must be recompiled on AIX 5L Version 5.2. In addition, existing 32-bit kernel extensions and device drivers used by 64-bit applications might have to be modified in order to support the new 64-bit ABI.
- **Kernel Extensions.** Kernel extensions for the 64-bit kernel run in 64-bit mode and have the scalability of the larger kernel address space. Some kernel services available in the 32-bit kernel are no longer provided by the 64-bit kernel, so existing 32-bit kernel extensions may have to be ported in order to be used with the 64-bit kernel.

Existing 32-bit kernel extensions continue to be supported by the 32-bit kernel, but these kernel extensions are not usable by the 64-bit kernel. Not all of the kernel extensions supported for the 32-bit kernel are supported for the 64-bit kernel, particularly the device drivers for the I/O.

- **Dual-mode Kernel Extensions.** AIX 5L Version 5.2 supports dual-mode kernel extensions, which can be loaded by a common configuration method, regardless of which kernel is being used. A dual-mode kernel extension is an archive file that contains both the 64-bit and 32-bit versions of the kernel extension as members.
- **Installation and Enablement.** The 32-bit and 64-bit kernels are provided as part of the AIX 5L Version 5.2 base media and are installed on all supported hardware systems. By default, the 32-bit kernel is enabled during base system installation. However, you can override this at installation time to enable the 64-bit kernel through the system installation panels.

You can switch between the 32-bit and 64-bit kernels without reinstalling the operating system.

1. Modify the `/usr/lib/boot/unix` directory and the `/unix` directory to be a symbolic link to the binary for the desired kernel.
2. Run the `bosboot` command to write a new system boot image.
3. Reboot the system.

The path name of the 64-bit kernel is `/usr/lib/boot/unix_64`, the path name of the uniprocessor is `/usr/lib/boot/unix_up`, and the path name of the multiprocessor versions of the 32-bit kernel is `/usr/lib/boot/unix_mp`.

## JFS2 File System Freeze and Thaw Feature

A new feature for the JFS2 file system is added to AIX 5L Version 5.2 with the 5200-05 Recommended Maintenance package. This feature provides an external interface whereby an application can request that a JFS2 file system freeze, or stay quiescent. After the freeze operation, the file system must remain quiescent until it is thawed or until the specified timeout has past.

The request for freeze or thaw can be performed from the command or from the API as follows:

- **Command:**

```
chfs -a freeze=<timeout or "off"> <file system name>
chfs -a refreeze=<timeout> <file system name>
```

- **API:**

```
fscntl()
```



## Enabling and Disabling DMAPI on a JFS2 File System

The DMAPI can only be enabled on a JFS2 file system using Version 1 Extended Attributes. Using the **chfs** command to enable the DMAPI on a JFS2 file system using Extended Attributes Version 2 or to change a DMAPI-enabled JFS2 file system to use Extended Attributes Version 2 fails with an error message.

You can disable the DMAPI on a JFS2 file system by typing the following:

```
chfs -a managed=no /fs_name
```

This command is supported only on an unmounted file system. If you try to disable the DMAPI on a mounted file system, the command fails with an error message.

## DMAPI and System or Volume Group Backup and Restore

The system and volume group backup commands, **mksysb**, **savevg**, and **mkcd**, by default, do not back up files within a DMAPI-enabled file system. The file systems are re-created on restoration of the backup, but no data is restored. If you want to back up the files, add a **-A** flag to the **mksysb**, **savevg**, or **mkcd** command.

Additionally, on restoration, DMAPI file systems are mounted as **nomanager** (without a manager application).

For more information, see the **/usr/lpp/bos.sysmgmt/README** file.

## Korn Shell Compatibility

In addition to the default system Korn shell (**/usr/bin/ksh**), AIX provides an enhanced version available as **/usr/bin/ksh93**. This enhanced version is mostly upwardly compatible with the current default version and includes a few additional features that are not available in **/usr/bin/ksh**. Some scripts may perform differently under **ksh93** than under the default shell, as variable handling is somewhat different under the two shells.

## Known Problems with ksh and ksh93 Commands

With the **ksh** command, when multiple shells have the **noclobber** option set and they redirect output to the same file, there could be a race condition which can result in multiple shell processes writing to the file. The shell does not detect or prevent such race conditions.

If the right-hand pattern of a regular expression contains the at (**@**) or vertical bar (**|**) characters used with their special meaning, the expression may not be properly evaluated. In this case, use the **/usr/bin/ksh93** command.

With the **/usr/bin/ksh93** command input redirection, using the "here document" may not be successful. To work around this problem, use the **/usr/bin/ksh** command.

During login shell startup, the following files are processed in the order specified:

1. **/etc/environment**
2. **/etc/profile**
3. **.profile**
4. **.env**

## JFS2 Log Attribute is Listed under JFS in the chfs Command

The *AIX 5L Version 5.2 Commands Reference, Volume 1* for the **chfs** command incorrectly lists the JFS2 log attribute under JFS. The correct information for JFS is:

### **-a log=LVName**

Specifies the full path name of the file system-logging logical volume name of the existing log to be used. The log device for this file system must reside on the same volume group as the file system.

The correct information for JFS2 is:

### **-a log=LVName**

For a file system using the outline log, you can use this option to change the outline log from one logical volume to another logical volume if the logical volume is properly formatted and if the type of the logical volume is `jfs2log`. If a file system is mounted at the time the **chfs** command is called to change the outline log, the **/etc/filesystems** file will indicate the change. However, the actual log will not be changed until the next mount for the file system, which follows a **umount** operation or a system crash and recovery.

For a file system using the inline log, this option does not support switching logs between the inline and the outline log. To switch from **inline** to **outline** (or vice versa), you must remove and re-create the file system.

## **New Flag for the `mkiv` Command**

- T O** Uses a new device sub type of logical volume. An application (such as a database) may use this new device sub type as an indication that it may safely stop skipping the logical volume control block (lvcb) at the beginning of the logical volume (lv).

## **The `-V` Flag for the `sar` Command not Supported**

The `-V` flag for the `sar` command is not supported on AIX 5.1 and later.

## **Perl**

**Note:** IBM continues to ship Perl, but does not support it.

The following Perl filesets are included with AIX pursuant to the terms of the artistic license:

- **perl.rte** 5.8.0 (version 5.8)
- **perl.man.en\_US**

For more information, run the **perl -v** command. To view the artistic license, see the following Web site:

<http://www.opensource.org/licenses/artistic-license.html>

The **perl.rte** fileset is automatically installed.

For more information about Perl, see the following Web site:

<http://www.perl.org>

The new Perl man pages are now located in the **/usr/opt/perl5/man** directory and the **/usr/opt/perl5/man64** directory.

AIX 5L Version 5.2 introduces Perl 5.8.0. If you have a Perl external subroutine compiled on earlier versions of Perl, the external subroutine may need to be recompiled with threading enabled on Perl 5.8.0.

## C99 Language Interfaces

AIX 5L Version 5.2 system libraries and headers include interfaces required by the ISO/IEC 9899:1999(E) (C99) language standard and the Single UNIX<sup>®</sup> Specification, Version 3. Some of the interfaces may have the same names as symbols in existing programs. The interfaces may be hidden by specifying the `-D_NOISOC99_SOURCE` when you are compiling.

Most of the new C99 language interfaces are unavailable when compiling to use the 128-bit long double floating point format rather than the default 64-bit long double format.

Domain errors generally do not occur for math routine error conditions.

## IBM 32-bit SDK for AIX, Java 2 Technology Edition, Version 1.4

IBM 32-bit SDK for AIX, Java 2 Technology Edition, Version 1.4 is released in **Java14.\*** filesets. For more information, see the `/usr/java14/docs/sdkguide.aix32.htm` file.

IBM 32-bit SDK for AIX, Java 2 Technology Edition, Version 1.4 is included with the AIX base operating system. The 64-bit version is available on both the AIX 5L Version 5.2 Expansion Pack and the AIX Java Web site at <http://www.ibm.com/developerworks/java/jdk/aix>.

You can dynamically reconfigure a logical partition (LPAR) running a Java 1.4 application.

**Note:** Decreasing the number of CPUs or real memory allocated to an LPAR will likely degrade the performance of a Java application, but the application should continue to run.

IBM AIX Developer Kit, Java 2 Technology Edition, Version 1.3.1, 32-bit version for POWER and IBM AIX Developer Kit, Java 2 Technology Edition, Version 1.3.1, 64-bit version for POWER are both supported on AIX 5L Version 5.2. You can download these products from the AIX Java Web site. Install all of the Java service refreshes. To see if a more recent refresh is available:

1. Go to the developerWorks<sup>®</sup> Web site at <http://www.ibm.com/developerworks/java/jdk/aix>.
2. Select the **Download and service information** link.
3. Select the **Fix Info** link from the **Java 1.3.1 32-bit** column or the **Java 1.3.1 64-bit** column.

As with Java 1.4, you can dynamically reconfigure an LPAR running Java 1.3.1.

## AIX Web Browser Transition to Mozilla

This version of AIX 5L Version 5.2 introduces support for the Mozilla 1.7.3 Web browser as the new default browser for AIX.

This AIX 5.2 maintenance package does not automatically change the default browser to Mozilla for existing AIX 5.2 installations. Instead, it adds Mozilla as an option to the system management tools to help facilitate this task.

Installation images for Netscape Communicator Version 4 are not available as a Web download or included on the *AIX 5L Version 5.2 Expansion Pack CD*.

The Mozilla Web browser for AIX is available on a CD that can be ordered with AIX, or it can be downloaded from the following Web site:

<http://www.ibm.com/servers/aix/browsers>

Mozilla for AIX requires GNOME libraries, which are available on the *AIX Toolbox for Linux Applications* CD or from the following Web site:

<http://www.ibm.com/servers/aix/products/aixos/linux>

## Installing Mozilla for AIX

Starting with AIX 5L Version 5.2 with the 5200-04 Recommended Maintenance package, Mozilla for AIX can be installed as an option during the AIX Base Operating System installation process, or it can be installed later. All listed installation methods use the Mozilla installation bundle, which includes Mozilla and the required GNOME libraries.

The Mozilla installation process fails if the required GNOME libraries are not found. The required rpm filesets are listed.

Use one of the following installation methods:

- Install Mozilla using the following AIX Base Operating System installation process:
  1. Select Mozilla for installation during the AIX Base Operating System installation process by selecting these options in the following order:
    - a. 2 = Change/Show Installation Settings and Install
    - b. 3 = More Options
    - c. 6 = Install More Software
    - d. 1 = Mozilla (Mozilla CD)

The default setting is to not install Mozilla.
  2. When prompted to do so, insert the *Mozilla* CD and the *AIX Toolbox for Linux Applications* CD.
- Install Mozilla as a bundle using the following Configuration Assistant process:
  1. Start **configassist**.
  2. Select **Manage software**, and click **Next**.
  3. Select **Install additional software**, and click **Next**.
  4. Select **Install by bundle**, and click **Next**.
  5. Specify the device or directory that contains the installation images, and click **Next**. If the location is a directory, such as **/usr/sys/inst.images**, verify the following:
    - The **Mozilla.base** installp package is in the **/usr/sys/inst.images/installp/ppc** directory
    - The toolbox rpm filesets are in the **/usr/sys/inst.images/RPMS/ppc** directory
  6. Select the Mozilla bundle, and click **Next**.
  7. Accept the license agreement, and click **Next** to start the installation process.
- Install Mozilla as a bundle using the following **smit** process:
  1. Run the **smit install\_bundle** command.
  2. Specify the **INPUT device/directory** for software. If the location is a directory, such as **/usr/sys/inst.images**, verify the following:
    - The **Mozilla.base** installp package is located in the **/usr/sys/inst.images/installp/ppc** directory
    - The toolbox rpm filesets are located in the **/usr/sys/inst.images/RPMS/ppc** directory
  3. Select the **Fileset Bundle = Mozilla**.
  4. In the Install Software Bundle screen, accept the license agreement, and press Enter to start the installation process.

## Configuring Mozilla as the Browser for AIX Documentation Services

Mozilla can be configured as the default browser that is used to view the AIX Documentation using Configuration Assistant or **smit**:

- Configure Mozilla using the following Configuration Assistant process:
  1. Start **configassist**.
  2. Select the Configure documentation server task.
  3. If Mozilla is detected as already installed, select **Yes, use Mozilla as the default browser**, and click **Next**.

- Configuring Mozilla using the following **smit** process:
  1. Run the **smit change\_default\_browser** command.
  2. Specify **mozilla** or **/usr/bin/mozilla** as the Default browser LAUNCH COMMAND.

## License Use Management (LUM) Commands

### Location Change for the LUM Commands

The location of the **i4blt**, **i4cfg**, **i4target**, and **i4tv** License Use Management commands has changed from the **/var/ifor** directory to the **/usr/opt/ifor/ls/os/aix/bin** directory.

**Note:** To configure LUM, use the **i4cfg -script** command.

The **/usr/lib/netls/conf** directory does not exist on AIX 5L Version 5.2. The only valid directory for the nodelock file is the **/var/ifor** directory.

### Change for the LUM Graphical User Interface (GUI)

AIX 5L Version 5.2 includes a new Java-based GUI. If you are migrating from AIX Version 4 to AIX 5L Version 5.2, you must install the **ifor\_ls.java.gui** fileset to use the new LUM GUI.

### New PRIVSEG\_LOADS Option for LDR\_CNTRL Tunable Parameter

Specifying the **PRIVSEG\_LOADS** option directs the system loader to put dynamically loaded private modules into the process private segment. This might improve the availability of memory in large memory model applications that perform private dynamic loads and tend to run out of memory in the process heap. If the process private segment lacks sufficient space, the **PRIVSEG\_LOADS** option has no effect. The **PRIVSEG\_LOADS** option is only valid for 32-bit applications with a non-zero **MAXDATA** value.

---

## Communications, Networking, and I/O

### 7135 RAIDiant Array for AIX Requirements after Installing AIX 5L Version 5.2

Customers installing AIX 5L Version 5.2 on systems with attached 7135-110 or 7135-210 RAIDiant Array subsystems must also obtain and install the latest version of controller and drive microcode. This microcode update can be obtained using hardware service channels (800-IBM-SERV in the U.S.) and by requesting ECA 010. You can also order the publication for the 7135, which is *7135 RAIDiant Array for AIX: Installation Guide and Reference*, that contains information about microcode and device driver installation.

### Enable Link Polling and Time Interval for Link Polling Configuration Attributes

The IBM 10/100 Mbps Ethernet PCI Adapter (Feature Code 23100020) does not have an interrupt-driven mechanism to tell the device driver of any changes in its link state.

To avoid this drawback, the device driver now provides an ODM attribute to determine the status of the link. This **Enable Link Polling** attribute is disabled by default. If this attribute is enabled, the device driver will poll the adapter every time period, equal to the time in milliseconds, specified in the **Time interval for Link Polling** attribute, for a change in the adapter's link state.

If the adapter's link is disabled for any reason, the device driver will disable its **NDD\_RUNNING** flag. When the device driver finds that the link is restored, it will enable this **NDD\_RUNNING** flag.

To work successfully, protocol layer implementations, such as EtherChannel, need notification if the link is disabled. Enable the **Enable Link Polling** flag for this adapter to send notification.

**Note:** The performance of this adapter will decrease if this flag is enabled, because of the additional PIO calls that the device driver makes to the adapter every few milliseconds while it determines the link status.

## Enhanced Error Handling (EEH)

EEH is an I/O error detection, reporting, and recovery mechanism to increase system availability from such errors. In the current implementation, the EEH mechanism can recover I/O errors on the PCI bus for most devices. Information about the faulty component and nature of the error (recoverable versus permanent) is logged in the AIX error log.

For EEH to work, your system must have the following:

- AIX kernel support. Systems with AIX 5L for POWER Version 5.1 with the 5100-04 Recommended Maintenance package (APAR IY44478) and AIX 5L Version 5.2 with the 5200-01 Recommended Maintenance package (APAR IY44479) or later systems have the latest EEH services.
- AIX device driver support (dds). Most dds has full EEH recovery (with a few exceptions).
- EEH-capable hardware.
- Appropriate system firmware levels.

Certain hardware and firmware requirements must be met for EEH to work on a given system. Refer to your system guides to determine if EEH will work on your system.

## Supported Devices

Device Driver support for EEH is limited to the following devices that are supported by AIX 5L Version 5.2:

- Storage Adapters:
  - Fibre Channel (6227)
  - Fibre Channel (6228)
  - Fibre Channel (6239)
  - PCI SCSI RAID Devices
  - PCI Ultra SCSI Devices
  - PCI Dual Channel Ultra3 SCSI Adapter (FC 6203)
  - PCI Dual Channel Ultra2 SCSI Adapter (FC 6205)
  - PCI-X Dual Channel Ultra320 SCSI RAID Adapter (5703, 5711)
  - PCI-X Dual Channel Ultra320 SCSI Adapter (5712, 5710)
- Communications and connectivity (PCI bus type):
  - Token-Ring PCI 4/16 Adapter (FC 2920 and 4959)
  - IBM Ethernet 10/100 Mbps (FC 2968)
  - 10/100 Mbps Ethernet PCI Adapter II (FC 4962)
  - IBM 4-Port 10/100 Base-TX Ethernet PCI Adapter (FC 4961)
  - 10/100/1000 Base-T Ethernet PCI Adapter (FC 2975)
  - Gigabit Ethernet (FC 2969)
  - TURBOWAYS® 622 Mbps PCI MMF ATM Adapter (FC 2946)
  - 2-Port Multiprotocol PCI Adapter (FC 2962)
  - 8-Port and 128-Port 232/422 Async PCI Adapters (FC 2943 and 2944)
  - IBM 64-bit/66 MHz PCI ATM 155 adapter (FC 4953 and 4957)
  - IBM Gigabit Ethernet-SX PCI-X Adapter (FC 5700)
  - IBM 10/100/1000 Base-TX Ethernet PCI-X Adapter (FC 5701)
  - IBM 2-Port 10/100/1000 Base-TX Ethernet PCI-X Adapter (FC 5706)
  - IBM 2-Port Gigabit Ethernet-SX PCI-X Adapter (FC 5707)



- S/390® ESCON® CHANNEL PCI ADAPTER (FC 2751)
- IBM ARTIC960HX 4-PORT PCI ADAPTER (FC 2947)
- IBM ARTIC960RXD QUAD DIGITAL TRUNK ADAPTER (FC 6310)
- Encryption Adapters:
  - IBM PCI Cryptographic Coprocessor (FC 4958 and 4963) \*
  - IBM eBusiness Cryptographic Accelerator (FC 4960) \*
- Graphics and Miscellaneous
  - GXT135P Graphics Adapter (FC 2848) \*
  - USB Open Host Controller (FC 2737) \*
  - GXT4500P (FC 2842)\*
  - GXT6500P (FC 2843)\*

**Note:** The devices above that are denoted with an asterisk (\*) require the user to intervene and manually recover the device after a bus error is encountered (for example, through device reconfiguration). Also, you may need to reboot Graphics and USB devices because those devices may not completely recover. If the device encounters an error during the configuration process, the device will be left in the defined state until there is a subsequent configuration attempt.

## EtherChannel

The EtherChannel backup function and the existing network interface backup (**netif\_backup**) function are supported on all Ethernet adapters.

Support for Ethernet adapters is provided in the form of fixes in the current release. The APAR numbers for these fixes are as follows:

10/100 Mbps Ethernet PCI Adapter II (1410FF01)

- APAR IY34820

10/100/1000 Base-TX PCI-X Adapter (14106902) and Gigabit Ethernet-SX PCI-X Adapter (14106802)

- APAR IY34821

10/100/1000 Base-T Ethernet PCI Adapter (14100401) and Gigabit Ethernet-SX PCI Adapter (14100401)

- APAR IY34822

## Gigabit Ethernet-SX PCI Adapter and IBM 10/100/1000 Base-T Ethernet PCI Adapter

The Gigabit Ethernet-SX PCI Adapter and the IBM 10/100/1000 Base-T Ethernet PCI Adapter share the same device driver. Therefore, the device driver and diagnostic package can be obtained by installing the **devices.pci.14100401** fileset. The device driver conditionally switches code that is unique for either adapter.

**Note:** The **lslpp** output for the **devices.pci.14100401** fileset (shown below) refers to the Gigabit Ethernet-SX PCI Adapter, although the fileset is shared by both adapters:

```
# lslpp -L | grep devices.pci.14100401
devices.pci.14100401.diag 5.2.0.0 C Gigabit Ethernet-SX PCI Adapter
devices.pci.14100401.rte 5.2.0.0 C Gigabit Ethernet-SX PCI Adapter
```

## Gigabit Ethernet Fast Port Failover

The Gigabit Ethernet Fast Port Failover function enables the IBM 2-Port 10/100/1000 Base-TX Ethernet PCI-X Adapter or the IBM 2-Port Gigabit Ethernet-SX PCI-X Adapter to be deployed in a primary/backup mode, where one port of the adapter is configured as the primary port, and the other port is configured as

the backup port. In the event of a link failure, the primary port fails over automatically to the backup port. The failover time is significantly less than EtherChannel failover (typically less than 1 second). Because some packet loss might occur at the time of the failover, a reliable protocol, such as TCP, should be used in conjunction with this function.

## IPX/SPX Protocol Support

IPX/SPX protocol support is provided in the **ipx.base** package. The **ipx.base** package is supported on the 32-bit kernel only.

## Removal of Support for Devices

The following devices are not supported on AIX 5L Version 5.2 with the 5200-05 Recommended Maintenance package:

- **PCI FDDI I/O** (FC 2741, FC 2742, and FC 2743) is not supported on AIX 5L Version 5.2 with the 5200-01 Recommended Maintenance package or later.
- **devices.pci.b7105090**. The Ethernet adapter that is supported by the **devices.pci.b7105090** fileset in AIX versions *prior* to AIX 5L Version 5.1 is *not* supported in AIX 5L Version 5.2. After a migration to AIX 5L Version 5.2, or when AIX 5L Version 5.2 is installed and this Ethernet adapter is in the machine, the following messages may display on the console or be written to log files:

```
Method error (/usr/lib/methods/cfgv3boom -l ent1 ):
    0514-068 Cause not known.
```

```
cfgmgr: 0514-621 WARNING: The following device packages are required for
device support but are not currently installed.
```

```
devices.pci.b7105090 Not found on the installation media.
```

Remove the unsupported Ethernet adapter from the machine. This adapter will not be configured by AIX 5L Version 5.2.

## The devices.artic960.5.2 Fileset

The **devices.artic960.5.2** fileset provides support for the following IBM ARTIC960 adapters:

- S/390 ESCON Channel PCI Adapter (FC 2751)
- IBM ARTIC960Hx 4-Port Selectable PCI Adapter (FC 2947)
- IBM ARTIC960RxD Quad Digital Trunk Adapter (FC 6310)

This includes EEH support and 64-bit support for FC 2751, FC 2947, and FC 6310 adapters. If an additional fileset is installed to access a particular IBM ARTIC960 adapter, full EEH and 64-bit support depends on the ability of the additional fileset to support EEH and 64-bit.

When you are upgrading to AIX 5L with 5200-05 on an existing AIX 5.2 system and a new PCI IBM ARTIC960 adapter is installed, support is provided on an Additional Device Software Support (*MES*) CD that is included with the PCI IBM ARTIC960 adapter. The **devices.artic960** fileset should then be upgraded to level 5.2.0.40.

Included with the **devices.artic960.5.2** fileset are the following filesets:

- **devices.artic960.rte**, IBM ARTIC960 Runtime Support
- **devices.artic960.unicode**, IBM ARTIC960 Adapter Software
- **devices.artic960.diag**, IBM ARTIC960 Adapter Diagnostics

When the **devices.artic960.5.2** fileset is installed, several pseudo-filesets will also be installed to aid in the automatic creation of various ARTIC devices. These new filesets are the following:

- **devices.pci.14104300.rte**, IBM ARTIC960 Device Runtime Support
- **devices.pci.14103600.rte**, IBM ARTIC960 PCI Device Runtime Support
- **devices.pci.86806019.rte**, ARTIC960 RP/RXD (ARTIC960RxD) Device Runtime Support



When a PCI I/O error occurs on an IBM PCI ARTIC960 adapter, the adapter slot becomes unavailable, and the IBM ARTIC960 adapter can be reset. Following an EEH error, the adapter software needs to be downloaded to the adapter again.

To determine if an EEH error occurred on an IBM ARTIC960 adapter, inspection of the error log is necessary. A temporary EEH error on an IBM ARTIC960 adapter is logged as a temporary EEH error followed by I/O errors specific to the IBM ARTIC960 adapter. Recovery from a temporary EEH error is accomplished by removing the IBM ARTIC960 device driver and making the adapter again using the **rmdev** and **mkdev** commands. This process loads the necessary adapter software onto the adapter.

If the error log shows a permanent EEH error, you must use the hot plug manager to remove the adapter and make the adapter again.

## The devices.pci.14108c00 Fileset

The **devices.pci.14108c00** fileset provides support for synchronous data link control (SDLC) and bi-synchronous protocols on the IBM ARTIC960Hx 4-Port Selectable PCI Adapter (FC 2947). When combined with the installation of the **devices.artic960** fileset, Enhanced Error Handling (EEH) support is provided. Either 32-bit or 64-bit kernel mode is supported. Applications that are 32-bit are supported.

## Missing Resource Processing

In a partitioned environment, missing resource processing (through the **diag -a** command) is not performed for processors, memory, L2 Cache, integrated devices, or pluggable adapters that have been moved to another partition. This is done to aid configuration for resources that are moved from one partition to another partition, then moved back to the original partition.

To remove a device from the configuration, log in as the root user, and type **rmdev -d1 device** at a command prompt, where *device* is the name of the device you want to remove.

For more information, view the service hints section within diagnostics when you are logged in as the root user or using the CE login. You can view the service information by doing the following:

1. At the command line, type **diag**.
2. When **Diagnostic Operating Instructions** is displayed, press Enter.
3. At the Function selection menu, select **Task Selection**.
4. At the Task Selection menu, select **Display Service Hints** and press Enter.

## IBM Directory (LDAP)

To access the latest IBM Directory, Version 4.1.0.0 product information, go to the following Web site:

<http://www.ibm.com/software/network/directory/>

## Installation and Configuration

For information specific to IBM Directory installation and configuration, go to the following Web site:

<http://www.ibm.com/software/network/directory/library>

From the **IBM Directory Server** category on this Web site, click **Product Manuals and Technical Documentation > Version: 4.1**. Read the following documents:

- *Installation and Configuration Guide for Multiplatforms*
- *Server Readme*
- *Client Readme*
- *Readme Addendum*

Before you run **ldapxcfg**, verify that the following links exist by typing the following commands:

```
/usr/ldap/db2 -> /usr/lpp/db2_07_01  
/usr/ldap/lib/libdb2.a -> /usr/lpp/db2_07_01/lib/libdb2.a
```

If these links are not present, create these links by typing the following commands:

```
ln -s -f /usr/lpp/db2_07_01/lib/libdb2.a /usr/ldap/lib/libdb2.a  
ln -s -f /usr/lpp/db2_07_01 /usr/ldap/db2
```

**Installing DB2 UDB7.2:** If you are reinstalling, force installing, or installing an update to the DB2® UDB 7.2 **db2\_07\_01.msg.ja\_JP** fileset, you should first remove the **db2\_07\_01.msg.Ja\_JP** and **db2\_07\_01.msg.ja\_JP** filesets.

**Directory Management Tool (DMT):** It is strongly recommended that you run DMT when you are logged in as a user without root authority.

## Administration

After installation of the **ldap.client** package, create the following link:

```
ln -s -f /usr/ldap/lib/aix5/libldapiconv64.a /usr/lib/libldapiconv64.a
```

## IBM Directory with Ja\_JP Locale

In the Japanese environment, it is strongly recommended that you use IBM Directory in the Ja\_JP locale. In other Japanese locales, the Server Administration GUI does not work properly.

## Dynamic Tracking and Fast I/O Failure of Fibre Channel Devices

AIX supports Dynamic Tracking and Fast I/O Failure of Fibre Channel Devices.

Dynamic Tracking allows the user to perform certain prescribed storage area network (SAN) changes that result in N\_Port ID changes (such as cable movement at the switch ports or the creating of inter-switch links) without taking devices offline.

Fast Fail causes I/Os down a particular link to fail faster due to lost links between the switch and the storage device. This may be useful in a multipath environment where you want I/Os to fail over to another path relatively quickly.

Support for these two features can be obtained by installing APAR IY37183. This APAR will install the **/usr/lpp/bos/README.FIBRE-CHANNEL** file. More information concerning these features is in this readme file.

Independent Software Vendors (ISVs) developing kernel extensions and/or applications that communicate with the AIX Fibre Channel Driver stack should refer to the Fibre Channel Protocol for SCSI and iSCSI Subsystem article in *AIX 5L Version 5.2 Kernel Extensions and Device Support Programming Concepts* for changes necessary to support Dynamic Tracking.

**Note:** Pay special attention to the *Required FCP and iSCSI Adapter Device Driver ioctl Commands* and *Understanding the scsi\_buf Structure* sections.

## Internet Protocol (IP) over Fibre Channel

This information supplements the "Internet Protocol (IP) over Fibre Channel" section in the *AIX 5L Version 5.2 System Management Guide: Communications and Networks*.

To set up the Fibre Channel networking capability between AIX and Thomson Grass Valley™ Media Servers (such as Profile PVS 1000), note that feature 6228 (IBM 2 Gigabit Fibre Channel Adapter for 64-bit PCI Bus) is currently the only Fibre Channel adapter supported for this configuration. In addition, the following steps are recommended to establish the communication between the two host systems:

1. Disable FARP (Fibre Channel Address Resolution Protocol) on AIX. For example, if the IP over Fibre Channel protocol driver instance is `fcnet0`, type the following command:

```
chdev -l fcnet0 -a enable_farp=no
```

2. If the Profile Media Server is set up to disable "checksum and re-transmit on error" (this is the default option), type the following command on the AIX command line, assuming fc0 is the interface for this purpose:

```
ifconfig fc0 tcp_disable_cksum
```

You can also use the AIX `ifconfig fc0` command to verify whether TCP checksum is disabled. To re-enable the TCP checksum on the IP over Fibre Channel interface, type the following command:

```
ifconfig fc0 -tcp_disable_cksum
```

APAR IY49409 is required for these **ifconfig** command options.

3. It is recommended that initial communication always be established from AIX with the **ping** command. Initiating the exchange (pinging) from the Profile Media Server, prior to any exchange over Fibre Channel from the AIX side, might result in a prolonged delay in the establishment of communication between the two systems.
4. For TCP/IP over Fibre Channel, set the **tcp\_sendspace** network option to a value which is at least equal to a device's Maximum Transfer Unit (MTU). Values higher than the MTU are preferred, but not mandatory.

IBM is working to resolve these limitations.

## Switch Network Interface (SNI)

Switch Network Interface (SNI) provides AIX support for the eServer pSeries High Performance Switch (HPS). The HPS communication subsystem is a network data technology based on the architecture of SP™ Switch and SP Switch2. HPS is supported on IBM eServer pSeries 690 and 655 clustered servers.

For more information, see *Switch Network Interface for @server pSeries High Performance Switch Guide and Reference*.

## AIX iSCSI Software Initiator

Beginning with AIX 5L with 5200-03, the iSCSI protocol driver is included as part of AIX Base Operating System. The iSCSI protocol allows the access of storage devices over gigabit Ethernet TCP/IP networks. The iSCSI support is in the filesets **devices.iscsi\_sw.rte**, **devices.iscsi.disk.rte**, and **devices.common.IBM.iscsi.rte**. These filesets supersede the **iscsi\_sw.rte** fileset that was previously included in the AIX Bonus Pack.

To use the iSCSI protocol driver, add the names of the iSCSI targets being accessed to the **/etc/iscsi/targets** file. For more information about configuring iSCSI, see the "iSCSI Software Initiator" section in the *AIX 5L Version 5.2 System Management Guide: Communications and Networks*. For more information about the **/etc/iscsi/targets** file, see the *AIX 5L Version 5.2 Files Reference*.

The AIX iSCSI protocol driver supports the 1-port and 2-port gigabit Ethernet adapters with optical or copper connections (FC 5700, FC 5701, FC 5706, and FC 5707). The iSCSI protocol driver is verified to work with the Cisco MDS 9000 IPS module as the iSCSI target, attaching to the IBM TotalStorage ESS F20 and IBM TotalStorage ESS 800 storage devices.

The current iSCSI protocol driver implements the draft-20 version of the IETF iSCSI standard, with the following limitations:

- During installation, the iSCSI driver creates a default initiator name. However, this generated iSCSI name might not comply with the format specified by the iSCSI String Profile document. You can use the iSCSI SMIT panels (under **smit iscsi**) to change the initiator name to comply with the standard or to match local iSCSI name conventions.

- The iSCSI protocol driver can connect to a maximum of 16 unique targets at one time. If fewer targets are in use, you can change the **Maximum Targets Allowed** field in the SMIT panel to reduce memory usage by the iSCSI driver.
- This implementation of iSCSI supports only one TCP/IP connection per iSCSI session.
- This implementation of iSCSI does not support redirection of iSCSI logins. Any received login response with a status class code of 01 is equivalent to a login failure.

---

## System Management

### Cluster Systems Management (CSM)

You can access the CSM documentation from the following Web site:

<http://www.ibm.com/servers/eserver/clusters/library>

Click the **AIX cluster software documentation** link, and then click the **Cluster Systems Management** link.

**Note:** Before you install CSM, you must read the *Software Planning and Installation Guide* for specific procedural steps to use when you are installing CSM. Installation of this product is not possible if you do not use the documented procedures in this book.

CSM Server requires four open-source rpm filesets that must be installed prior to installing the CSM Server software and its dependent packages, the CSM Distributed Command Execution Manager (DCEM) GUI and the CSM DCEM Web-based System Manager application. The required rpm filesets are:

- tcl
- tk
- expect
- conserver

As the root user, do the following to install the rpm filesets and the CSM Server:

1. Install the above rpm filesets using SMIT Install Software (type **smitty install\_latest** at the AIX command line).
  - a. Press F4, and select **/dev/cd0** (CD Drive) as the **INPUT device / directory for software**.
  - b. Press F4, and select (by pressing F7 for each package) **tcl-8.3.3**, **tk-8.3.3**, **expect-5.32**, and **conserver-7.2.4** as the **SOFTWARE to install** values, or press F4 and select all the software packages you want.
  - c. To accept the software license agreements, press the Tab key to change no to yes as the **ACCEPT new license agreements** value, and then press Enter.
  - d. Press Enter again to confirm that you want to continue the installation process.
  - e. Review the installation results, and press F3 to return to the installation panel, or press F10 to return to the AIX command line.
2. Install the CSM Server and its dependent software using SMIT Install Software (type **smitty install\_latest** at the AIX command line).
  - a. Press F4, and select (by pressing F7 for each package) **csm.server**, **csm.gui.dcem**, and **csm.gui.websm** as the **SOFTWARE to install** values, or press F4 and select all the software packages you want.
  - b. To accept the software license agreements, press the Tab key to change no to yes as the **ACCEPT new license agreements** value, and then press Enter.
  - c. Press Enter again to confirm that you want to continue the installation process.
  - d. Review the installation results, and press F3 to return to the installation panel, or press F10 to return to the AIX command line.

## Software Requirements

The following software is required for CSM:

- CSM for AIX 5L, Version 1.4 (5765-F67)

The following APAR is required for CSM on AIX 5L Version 5.2 nodes:

- IY58079 (RSCT for AIX 5.2)

The following APAR is required for CSM on AIX 5L Version 5.1 nodes:

- IY34707

The cluster management server must be a pSeries machine running AIX 5L Version 5.2. The other machines within the cluster are referred to as managed nodes and can be pSeries machines running AIX 5L Version 5.2, or AIX 5L for POWER Version 5.1 with the 5100-03 Recommended Maintenance package.

The cluster management server must be a pSeries machine running AIX 5L Version 5.3 or AIX 5L Version 5.2 with the 5200-05 Recommended Maintenance package. Other machines within the cluster are referred to as *managed nodes* and can run AIX 5L Version 5.3, AIX 5L Version 5.2 with the 5200-05 Recommended Maintenance package and APARs as previously mentioned, or AIX 5L for POWER Version 5.1 with the 5100-07 Recommended Maintenance package. They can also be xSeries machines running CSM for Linux on e325 and xSeries Version 1.4.

## CD and DVD Automount Facility

AIX 5L Version 5.2 provides a CD and DVD automount facility (**cdromd**) with the **bos.cdmount** fileset. To have the **cdromd** daemon enabled on each system startup, add the following line to the **/etc/inittab** file:

```
cdromd:23456789:wait:/usr/bin/startsrc -s cdromd
```

The **cdromd** daemon can interfere with scripts, applications, or instructions that attempt to mount the CD or DVD device without first checking to see if the device is already enabled. A resource or device busy error occurs in this condition. Use the **cdumount** or **cdeject** commands to unmount the device so that you can mount the device as specified in the program or instructions. Alternatively, use the **cdcheck -m** or **mount** commands to determine the current mount point of the device.

For more information, see the **cdromd** command documentation in *AIX 5L Version 5.2 Commands Reference, Volume 2*, available at the pSeries Information Center located at the following Web site:

<http://publib16.boulder.ibm.com/pseries/index.htm>

### Notes:

1. To suspend the management of a device by the **automounter** daemon without causing the device to eject the media, type the following command, where *device* is the name of the device:

```
cdutil -s -k device
```

By default, when the **bos.cdmount** fileset is installed, the **cdromd** entry in the **/etc/inittab** file is not enabled.

2. The AIX 5L Version 5.2 system management documentation incorrectly states that CDs and DVDs are mounted by default.
3. When the **cdromd** command is enabled and an installation is performed that requires an additional volume, the CD is ejected, and you are prompted to enter the next volume. If this behavior is undesired, disable the **cdromd** command during installation. Normal behavior during multivolume installation is to unmount the CD and prompt for the next volume without ejecting the CD.

## SVR4 Printing

For information about configuring and setting up SVR4 printing, see the *Printing for Fun and Profit under AIX 5L* (IBM Redbook number SG24-6018-00) at the following Web site:

## Using the `mkprtdap` Command with IBM Directory 5.1

For IBM Directory 5.1 and later, the IBM Directory (LDAP) server must be installed and configured on the system before the `mkprtdap` command can be run to configure System V print-specific information. The `mkprtdap` command supports configuring an IBM Directory 4.1 server on the system if one has not been configured before. The initial Directory configuration that is supported by the `mkprtdap` command in IBM Directory 4.1 is configuring the Administrator's DN password and the DB2 database when they have not been configured before. This functionality is not supported by the `mkprtdap` command for IBM Directory 5.1 and later.

The `mkprtdap` command is supported only for IBM Directory 5.1 on AIX 5L Version 5.2 with the 5200-01 Recommended Maintenance package or later.

## Parallel Printer Cable Selection

The parallel printer cable must be changed to a cable that is IEEE1284-compliant if all of the following statements are true:

- Your system was manufactured after 1998.
- The printer is "parallel attached."
- The attached printer is not a dot-matrix printer.
- The output of the `lsdev -C -l ppa0` command contains the word IEEE1284.

If the output of the `lsdev` command contains the word Standard, or if the printer is a dot-matrix printer, an IEEE1284-compliant cable is not required.

Cables that are not IEEE1284-compliant may not correctly transmit data to high-speed printers. Loss of printer data may occur because the cables may not be capable of transmitting data at rates that are possible with newer ECP parallel ports.

## Web-based System Manager

### Remote Client Management

An HTTP Server must be installed and configured using one of the following configuration methods:

- Installing the IBM HTTP Server 2.0.47.1 on an AIX machine
- Installing any other HTTP Server on an AIX machine

This is necessary to support remote client management using Web-based System Manager. Proper configuration of an HTTP Server allows an AIX machine to serve the remote client download pages, Java Web Start, applet pages, and online extended helps.

When installing the IBM HTTP Server 2.0.47.1 on an AIX machine:

- Use the `wsm_remote` Software Bundle (`smitty install_bundle`) to install the IBM HTTP Server and required Documentation Library services software.
- Upon successful installation of the software, the bundle's post-installation processing script consolidates the steps needed to configure and initiate remote access and document serving capabilities for Web-based System Manager and the Documentation Library remote services.
- This multimedia installation bundle prompts you to have the AIX Expansion Pack media available to install the IBM HTTP Server and the AIX base media to install the Documentation Library filesets.
- If you obtained the IBM HTTP Server, Version 2.0.47.1 from the following IBM HTTP Server product Web site:

<http://www.ibm.com/software/webserver/httpserver/>



then the **wsm\_remote** Software Bundle allows you to install IHS from the hard disk by specifying the directory path name that contains your copy of the software installation images. To install IHS on AIX using the **wsm\_remote** Software Bundle, manually complete the setup as follows:

1. The installation directory path name must be in the format `./ismpppc/package_name`. For example, downloaded installation images can be copied to the `/usr/sys/inst.images/ismpppc/IHS2` directory. In this example, the installation source name is `/usr/sys/inst.images`, and the package name is **IHS2**.
2. The response file named **silent.res** must be linked to the name **IHS2.response** for AIX to detect automatic responses during a silent installation, such as specifying the **-P ihs.installLocation=/usr/HTTPServer** preferred AIX installation location and a language other than the default en (English) language.

When installing any other HTTP Server on an AIX machine, complete the following:

1. Install the Web server.
2. Upon successful installation of the software, configure the Web server using the **smitty change\_doc\_search\_server** SMIT fast path command.
3. Select **Local - this computer** as the value for "Documentation search server LOCATION," and provide the required information in the subsequent panels. A configuration script runs and consolidates the steps needed to configure and initiate remote access and file-serving capabilities for Web-based System Manager.

## Configuration Assistant

The Configuration Assistant displays after an AIX base installation completes. Some preliminary configuration is performed during the base installation that was intended to simplify subsequent configuration of the Web server.

The Configuration Assistant task titled "Configure a web server to run Web-based System Manager in a browser" seems to detect the IBM HTTP Server in the path `/usr/HTTPServer/htdocs`.

However, Web server software is not installed as part of the AIX base processing. You must first install a Web server and then return to this task to properly complete the configuration.

After successful installation of any HTTP server, you may bring up the Configuration Assistant using the **configassist** command from within a desktop window:

- Complete the task titled "Configure a web server to run Web-based System Manager in a browser" using the required information from the Web server software that was installed.

The alternate configuration methods are listed in the previous section, "Remote Client Management" on page 32. Either of those methods will also result in a correct Web server configuration that supports the Web-based System Manager remote environment.

## Distributed Command Execution Manager (DCEM)

The installation of the CSM DCEM GUI (**csm.dcem.gui**) and the CSM DCEM Web-based System Manager application (**csm.dcem.websm**) packages is dependent upon the installation of the CSM Server. See "Cluster Systems Management (CSM)" on page 30 for installation instructions.

## Pattern Matching

Several changes have been made to the pattern matching capability of the **Find** and **Filter** actions. The AIX 5.1 behavior of pattern matching was to locate a substring of the pattern. The AIX 5.2 behavior allows the use of one or more asterisk (\*) characters to represent complex pattern matches similar to the Korn shell.

Because of this change, patterns used in AIX 5.1 will not work the same in AIX 5.2. In AIX 5.1, a pattern of *abc* would match property values that contained the substring *abc*. In AIX 5.2, a pattern of *abc* will only match property values that are exactly *abc*. In order to get the AIX 5.1 behavior, specify the pattern as *\*abc\**.

In addition to the change in the pattern matching rules, the name of the pattern matching operator in the **Filter** dialog has changed from **contains** to **matches**.

### Viewing Remote Queue Status

In Web-based System Manager, the **All Print Queues** view for AIX remote printers can inaccurately indicate a problem with a remote queue. Check the actual status of the queue from the command line by typing the following command:

```
enq -q -P queue
```

If the command returns status indicating that the queue is ready, printing will function normally.

## Inventory Scout, Version 2.2.0.0

Inventory Scout, Version 2.2.0.0 provides support for the new POWER5 server family. The Vital Product Data (VPD) collection and formatting has changed significantly for this family of IBM servers, using the industry standard XML to encapsulate the VPD inventory data. These changes, for the most part, should be transparent to users of the system. The IBM tools and servers that receive VPD data are enhanced to use this new format. The new XML-formatted VPD does not support the concatenation of VPD files that the legacy format permitted.

Inventory Scout has a new microcode management graphical user interface (GUI). This feature is available on your AIX system by installing the **invscout.websm** fileset, or if a Hardware Management Console (HMC) is attached, by using the microcode update function. The GUI is a Web-based System Manager plug-in that surveys the microcode levels of the system, and, on POWER4 and POWER5 systems, downloads and installs microcode. Inventory Scout continues to work with the applet, to perform surveys only, at the following Web site:

<https://techsupport.services.ibm.com/server/aix.invscoutMDS>

This release of Inventory Scout significantly changes the method used to determine the microcode levels of systems, adapters, and devices to compare it to the latest available levels. Previously, data was collected and sent to IBM to determine the state of the system.

The new microcode management feature does the following:

- Downloads a catalog of available levels to the system being examined
- Conducts a microcode survey on the system and compares it to the latest available microcode
- Allows you to download and flash to the latest microcode available for POWER4 and POWER5 systems

The new microcode survey procedure might cause some problems with customer techniques used for surveying systems and might require changes to those procedures.

The microcode management feature relies on system features that were not present in previous generations of the systems. Support for microcode on these systems is limited to survey only. For more information about microcode updates, see the following Web site:

<http://techsupport.services.ibm.com/server/mdownload>

To enable the new Inventory Scout functionality, the following filesets must be installed at the following levels or higher:

<b>invscout.com</b>	2.2.0.0
<b>invscout.ldb</b>	2.2.0.0



<b>invscout.rte</b>	2.2.0.0
<b>invscout.websm</b>	2.2.0.0

To obtain the required filesets, order APAR IY58377 from the following Web site:

<http://www.ibm.com/servers/eserver/support/pseries/aixfixes.html>

If you are using the microcode management feature tool through the HMC, your HMC should be at Release 3, Version 3.0.

The HMC code can be obtained from the following Web site:

<http://techsupport.services.ibm.com/server/hmc/>

Customers who need to survey microcode levels on systems isolated from the Internet should go to the following Web site:

<https://techsupport.services.ibm.com/server/aix.invscoutMDS>

At the above Web site, pay special attention to the section "Two ways to use this service." The second bullet under that section addresses this issue.

## Known Problems

The following devices have limitations in the ability to update microcode with the microcode management feature:

- PCI 4-Channel Ultra3 SCSI RAID Adapter.
- CD-ROM and DVD-ROM Drives.
- RAID Devices.
- SSA devices and adapters.
- Inventory Scout will not properly handle some OEM adapters and devices. For more information, see "Obtaining the Firmware CD" on page 36.

For more information about these devices, see the readme files at the following Web site:

<http://techsupport.services.ibm.com/server/mdownload>

When you are updating system firmware from an HMC, the connection between the HMC and the system might not be synchronized. You can fix this problem by going to the server management panel on the HMC and selecting **Rebuild Managed System**.

Some adapters and devices do not support concurrent operation with microcode flashing. Such devices must be taken offline to update the microcode. This situation creates a problem when you are updating microcode for communications adapters used to communicate with the Internet to get the microcode updates or to communicate with an HMC. In this case, if the adapters are online and the update is attempted, the final step of flashing the device is not completed. You can complete the update procedure by taking the device offline and going into diagnostic service aids to download microcode to that device.

Due to the changes in how the survey works, you can no longer concatenate survey results prior to sending them to IBM.

There is a known system firmware upgrade problem with the IBM eServer pSeries 690 or the IBM eServer pSeries 670 machines that have six 7040-61D I/O drawers and three Integrated Battery Features (IBFs), or seven or more 7040-61D I/O drawers, regardless of the number of IBFs. Systems with this configuration should not use the new GUI for microcode management to update the system firmware. For additional information, refer to the 7040-681 and 7040-671 readme files which can be found at the following Web site:

<http://techsupport.services.ibm.com/server/mdownload>

## Obtaining the Firmware CD

Inventory Scout firmware management has problems with proxy servers and fire walls. If you are unable to successfully conduct a firmware survey, you may have problems accessing the Internet. The alternative to accessing the Internet for firmware fixes is to download the *Firmware* CD from the following Web site:

<http://techsupport.services.ibm.com/server/mdownload/cdimage.html>

## Tivoli Management Agent (TMA), Version 3.7.1.0

The foundation for the Tivoli Enterprise Software product suite and third-party management products is the Tivoli Management Framework. This framework provides the graphical desktop, object-oriented databases, and base services used by other management products. TMA is a less substantial version of the Tivoli Management Framework for installation on client systems.

For more information about Tivoli Systems products and services, including how to become a Tivoli Systems customer, do one of the following:

- Call 1-800-2TIVOLI to be connected to your local sales office
- Visit the Tivoli software page at the following Web site:

<http://www.ibm.com/software/tivoli/>

---

## Other Software

This section contains information about other software. Additional information about AIX-supported products is available from the following Web site:

<http://www.ibm.com/servers/aix/products/ibmsw/list/>

## Compilers

### VisualAge C++ Professional for AIX

VisualAge<sup>®</sup> C++ Professional for AIX, Version 6.0.0, is a fully supported version of this product. Install Version 6.0.0 by using your existing Version 6.0.0 CDs and applying APARs IY34533, IY34534, IY34536, IY34538, and IY34623 to complete the installation on AIX 5L Version 5.2.

VisualAge C++ Professional for AIX, Version 5.0.2, is a fully supported version of this product. Install Version 5.0.2 by using your existing Version 5.0.2 CDs and applying APARs IY34533, IY34534, IY34535, IY34537, and IY34623 to complete the installation on AIX 5L Version 5.2.

### C for AIX

C for AIX, Version 6.0.0 is a fully supported version of this product. Install Version 6.0.0 by using your existing Version 6.0.0 CDs and applying APARs IY34533, IY34534, IY34536, and IY34623 to complete the installation on AIX 5L Version 5.2.

C for AIX, Version 5.0.2 is a fully supported version of this product. Install Version 5.0.2 by using your existing Version 5.0.2 CDs and applying APARs IY34533, IY34534, IY34535, and IY34623 to complete the installation on AIX 5L Version 5.2.

### XL Fortran for AIX

XL Fortran for AIX, Version 8.1, is a fully supported version of this product. Install Version 8.1 by using your existing Version 8.1 CDs and applying APARs IY34533, IY34534, IY33757, IY33758, and IY34623 to complete the installation on AIX 5L Version 5.2.

XL Fortran for AIX, Version 7.1.1 is a fully supported version of this product. Install Version 7.1.1 by using your existing Version 7.1.1 CDs and applying APARs IY34533, IY34534, IY33755, IY33756, and IY34623 to complete the installation on AIX 5L Version 5.2.

## AIXlink/X.25

### AIXlink/X.25, Version 2.1

AIXlink/X.25 Version 2.1 is supported on AIX 5L Version 5.2 with the 5200-01 Recommended Maintenance package or later, which is included on the AIX Update CD, beginning with May 2003.

For more information about supported adapters and about configuration and installation, see the *AIXlink/X.25 Version 2.1 for AIX: Guide and Reference* at the following Web site:

<http://publib16.boulder.ibm.com/pseries/index.htm>

### AIXlink/X.25, Version 2.0.2

AIXlink/X.25 Version 2.0.2 is supported on AIX 5L Version 5.2 with the 5200-01 Recommended Maintenance package or later, which is included on the AIX Update CD, beginning with May 2003.

For more information about supported adapters and about configuration and installation, see the *AIXlink/X.25 Version 2.0 for AIX: Guide and Reference* at the following Web site:

[http://publib16.boulder.ibm.com/pseries/en\\_US/infocenter/base/aix52.htm](http://publib16.boulder.ibm.com/pseries/en_US/infocenter/base/aix52.htm)

### AIXlink/X.25, Version 1.1.5

AIXlink/X.25 Version 1.1.5 is not supported on AIX 5L Version 5.2.

## AIX Fast Connect, Version 3.1.2

AIX Fast Connect documentation is available at the following Web site:

[http://publib16.boulder.ibm.com/pseries/en\\_US/aixbman/fastcon/fastcontfrm.htm](http://publib16.boulder.ibm.com/pseries/en_US/aixbman/fastcon/fastcontfrm.htm)

The latest updates of this product are described in the **/etc/cifs/README** file, which is installed with AIX Fast Connect.

### Quick Start

To install AIX Fast Connect:

1. Install AIX Fast Connect from the distribution CD using the **smitty install\_all** fast path.
2. Use the **smitty smb** fast path to access AIX Fast Connect SMIT menus.
3. Configure AIX Fast Connect for encrypted passwords, and add a user.
4. Access the AIX Fast Connect server from a PC client by mapping a network drive. The server name is the same as the AIX host name, and HOME share is available by default.

## Communications Server

If you are using Communications Server for Systems Network Architecture (CS/AIX or SNA) support, use the following level:

- Communications Server for AIX, Version 6.1 (6.1.0.0 or later)

**Note:** The AnyNet<sup>®</sup> functions of CS/AIX are not supported on the 64-bit kernel.

## DCE for AIX

DCE 3.1 for AIX is not supported on the 64-bit kernel.



---

## Chapter 3. Installing and Configuring a Secure System

This chapter is a supplement to the *AIX 5L Version 5.2 Security Guide*. It provides information relevant to configuring and using a system according to the requirements of CAPP/EAL4+ Common Criteria evaluation of AIX 5L 5200-06. The headings used are identical to those in the *AIX 5L Version 5.2 Security Guide* unless otherwise noted. Information here supersedes information in the *AIX 5L Version 5.2 Security Guide*.

---

### Controlled Access Protection Profile and Evaluation Assurance Level 4+ (CAPP/EAL4+)

#### CAPP/EAL4+ Compliant System Overview

AIX 5.2 with the 5200-06 Recommended Maintenance package is evaluated on IBM pSeries Symmetric Multiprocessor Systems using POWER5 CPUs (p5 520, p5 570, p5 595).

#### Installing a CAPP/EAL4+ System

After AIX 5200-04 is installed in CAPP/EAL4+ mode as described in the *AIX 5L Version 5.2 Security Guide*, it is necessary to upgrade to 5200-06 (Maintenance Level 6) and install three additional PTFs so that the system is properly configured. Steps 2 through 11 document how to download and install 5200-06 and steps 12 through 20 document how to download and install the additional PTFs. You must use the PRPQ number P91209 and feature code 5829. This provides 5200-04, 5200-06 and a copy of the Release Notes. Note that 5200-06 with the additional PTFs comprises the evaluated configuration.

1. Before upgrading to 5200-06 and installing the additional PTFs, it is necessary to run the following script. This script allows filesets to be installed on the system:

```
<BEGIN>
#!/usr/bin/ksh

umask 027
unset PATH
export PATH=/usr/bin:/etc:/usr/sbin:/sbin:/usr/ucb

# ignore signals to prevent inconsistent state
trap "" INT HUP TERM QUIT EXIT

cat << \EOF >/etc/odm.data
PdAt:
    uniquetype = ""
    attribute = "TCB_STATE"
    deflt = "tcb_enabled"
    values = ""
    width = ""
    type = ""
    generic = ""
    rep = ""
    nls_index = 0
EOF

#Allow libc to install
chmod u+x /usr/lib/methods/cfgsf

#remove CC_EVAL attr from ODM
odmchange -o PdAt -q "attribute=TCB_STATE" /etc/odm.data

#remove rsct.core.rmc co-rec from bos.rte
ODMDIR=/usr/lib/objrepos odmget -q lpp_name=bos.rte.control product | \
```

```
grep -v rsct.core.rmc | sed 's/\\n\\n\\n/"' > /etc/control.add
ODMDIR=/usr/lib/objrepos odmdelete -o product -q lpp_name=bos.rte.control
ODMDIR=/usr/lib/objrepos odmadd /etc/control.add
</BEGIN>
```

2. Use Download Director to securely download the filesets needed to upgrade to 5200-06. Go to Quick links for AIX at the following web site:

<http://www-912.ibm.com/eserver/support/fixes/search.jsp?system=2&release=5.2>

It is also possible to upgrade to 5200-06 by using an AIX Update CD (the date on the CD should be 05/2005). If an update CD is used, continue to step 12 for instructions on installing the additional PTFs required.

3. In the **Specific fixes** section, select **AIX 5.2**. In the **Search by** pull down box, select APAR number or abstract and type in the APAR IY67913 in the **Search string** box. Select **Go**.
4. Add the APAR to your download list by selecting it from the text box and selecting Add to my download list.
5. Select Continue.
6. On the **Packaging Options** page ensure that the **Include prerequisites and corequisites** and **Include ifrequisites** packaging options are checked. **Include fixes that correct regressions** and **Replace superseded fixes with the latest** should not be checked.
7. Select AIX 5200-04 from the pull down box.
8. Provide the output file for the **lspp -Lc** command in the **File location** box by selecting the **Browse** button and browsing to the location of the file.
9. Select **Continue**.
10. On the **Download fixes** page you have several options. Select Download all filesets using Java applet which starts the Download Director Java applet. You will have to grant the applet access to the system you are downloading the filesets to by responding to the pop-up dialog boxes in your browser.
11. Download and install the filesets using the Java applet. To install the filesets, place them in a directory on the system to be upgraded. In this example, the filesets are copied to the **/usr/sys/ml6** directory. Generate a **.toc** file using the **inutoc** command:

```
# inutoc /usr/sys/ml6
```

Once the **.toc** file has been generated, run the following command to invoke smitty to install the updates:

```
# smitty update_all
```

This upgrades the system to 5200-06. You must reboot the system. Verify that the system has been upgraded to 5200-06 by running the following command:

```
# oslevel -r
```

If the system was successfully ungraded, 5200-06 is displayed.

12. Use Download Director to securely download the additional PTFs. Go to Quick links for AIX at the following web site:  
<http://www-912.ibm.com/eserver/support/fixes/search.jsp?system=2&release=5.2>
13. In the **Specific fixes** section, select **AIX 5.2**. In the **Search by** pull down box, select Fileset or PTF number.
14. Search for and add the following PTFs to your download list: U802365, U802353, and U802354.
15. Select Continue.
16. On the **Packaging Options** page, ensure that the **Include prerequisites and corequisites** and **Include ifrequisites** packaging options are checked. **Include fixes that correct regressions** and **Replace superseded fixes with the latest** should not be checked. Note that additional filesets will be listed in your download list.

17. Ensure that 5200-06 is selected from the pull down box. It is not necessary to provide output from the **lspp -Lc** command to download these filesets.
18. Select Continue.
19. On the **Download fixes** page you have several options. Select Download all filesets using Java applet which starts the Download Director Java applet. You will have to grant the applet access to the system you are downloading the filesets to by responding to the pop-up dialog boxes in your browser. You can also obtain and install the updates from physical media.
20. Install the filesets you downloaded by placing them in a directory on the system to be upgraded. In this example, the filesets are copied to the **/usr/sys/capp\_updates** directory. Generate a **.toc** file using the **inutoc** command:

```
# inutoc /usr/sys/capp_updates
```

Once the **.toc** file has been generated, run the following command to invoke smitty to install the updates:

```
# smitty update_all
```

This command installs the additional PTFs. You must reboot the system after installing these PTFs. These PTFs correspond to the following filesets:

- U802365: bos.rte.security 5.2.0.63
- U802353: bos.mp64 5.2.0.62
- U802354: bos.mp 5.2.0.62

Use the **lspp** command to ensure these filesets are installed at the correct levels.

21. After installing these filesets, run the script below. This script restores the state of the system such that additional filesets cannot be installed and sets the file mode bits for various files so that the system is configured as required. This script can take a while to complete.

```
<BEGIN>
#!/usr/bin/ksh

umask 027
unset PATH
export PATH=/usr/bin:/etc:/usr/sbin:/sbin:/usr/ucb

# ignore signals to prevent inconsistent state
trap "" INT HUP TERM QUIT EXIT

cat << \EOF > /etc/odm_back.data
PdAt:
    uniquetype = ""
    attribute = "TCB_STATE"
    deflt = "CC_EVAL"
    values = ""
    width = ""
    type = ""
    generic = ""
    rep = ""
    nls_index = 0
EOF

#disable libc updates
chmod 000 /usr/lib/methods/cfgsf

#restore the ODM state
odmchange -o PdAt -q "attribute=TCB_STATE" /etc/odm_back.data

#patch evalify for CC
CC_SH=/usr/lib/security/CC_EVALify.sh
CC_OR=/usr/lib/security/CC_EVALify.sh.orig
mv $CC_SH $CC_OR
sed "s/|\\dev\\null/>\\dev\\null/g" $CC_OR >$CC_SH
```



```

chmod u+x $CC_SH

#execute evalify for CC
/usr/lib/security/CC_EVALify.sh

#remove some additional suid/sgid bits
set -A CHG_MOD\
    "/usr/bin/host"          "0555"\
    "/usr/bin/rexec"        "0555"\
    "/usr/bin/rlogin"       "0555"\
    "/usr/bin/setgroups"    "0555"\
    "/usr/bin/shell"        "0555"\
    "/usr/bin/lsrc"         "0555"\
    "/usr/bin/ps"           "0555"\
    "/usr/bin/smitacl"      "0555"\
    "/usr/bin/sp1p"         "0555"\
    "/usr/bin/w"            "0555"\
    "/usr/bin/w64"          "0555"\
    "/usr/lib/lpd/pio/etc/piomkapqd" "0555"\
    "/usr/lib/lpd/piobe"    "0555"\
    "/usr/sbin/killall"     "0555"\
    "/usr/sbin/lsgroup"     "0555"

i=0;
while [[ $i -lt ${#CHG_MOD[*]} ]] ; do
    file=${CHG_MOD[$i]}      ; i=$((i+1))
    mode=${CHG_MOD[$i]}     ; i=$((i+1))

    chmod $mode $file
    tcbck -a $file mode=$mode type
done

#check TCB database for any system updates
tcbck -p ALL
</BEGIN>

```

## System Configuration for a CAPP/EAL4+ System

The system, sys, adm, uucp, mail, security, cron, printq, audit and shutdown groups are considered administrative groups. Only trusted users should be added to this group.

### Hard disk erasure\*

AIX 5L 5200-06 allows hdisks to be erased via the **Format media** service aid in the AIX diagnostic package. The diagnostic package is fully documented in the *Diagnostic Information for Multiple Bus Systems* book, as well as your hardware user's guide.

To erase a hard disk run the following command:

```
diag -T "format"
```

This will start the **Format media** service aid in a menu driven interface. If prompted, select your terminal.

You will then be presented with a resource selection list. Select the hdisk devices you want to erase from this list and commit your changes according to the instructions on the screen.

Once you have committed your selections, select Erase Disk from the menu. You will then be asked to confirm your selection. Choose **Yes**.

You will be asked if you want to **Read data from drive** or **Write patterns to drive**. Select Write patterns to drive.

You will then have the opportunity to modify the disk erasure options. After you specify the options you prefer, select Commit Your Changes. The disk is erased. Note that it can take a long time for this process to complete.

\*This section does not currently exist in the *AIX 5L Version 5.2 Security Guide*.

---

## Auditing

### Event Selection

These audit events have been added to the events listed under **General System Administration Events**:

- **Starting the audit subsystem**
- **Stopping the audit subsystem**
- **Querying the audit subsystem**
- **Resetting the audit subsystem**

### Setting Up Auditing

Step 5: When you have finished making any necessary changes to the configuration files, you are ready to use the **audit start** command option to enable the audit subsystem. This will generate the AUD\_It event with a value of 1.

Step 6: Use the **audit query** command option to see which events and objects are audited. This will generate the AUD\_It event with a value of 2.

Step 7: Use the **audit shutdown** command option to deactivate the audit subsystem again. This will generate the AUD\_It event with a value of 0.



---

## Appendix A. AIX 5L Version 5.2 Unsupported Items

---

### AIX 5L Version 5.2 Unsupported Devices and Machines

The following devices and machines are not supported:

- RS/6000 or OEM hardware based on the MCA bus
- Scalable Parallel (SP) nodes based on the MCA bus
- RS/6000, Power Personal Systems, or OEM hardware based on the PReP architecture
- POWER1, POWER2™, POWER Single Chip (RSC), POWER2 Single Chip (P2RSC), and 601 and 603 processors
- PCMCIA device support
- PCI adapters:
  - 2408 F/W SCSI SE, PCI/SHORT/32BIT/5V
  - 2409 F/W SCSI DIFF, EXT ONLY, PCI/SHORT/32BIT/5V
  - 2638 VIDEO CAPTURE(NTSC/PAL/SECAM), PCI/LONG/32BIT/5V
  - 2648 (GXT150P) PCI/SHORT/32BIT/5V, GRAPHICS ADAPTER
  - 2657 S15 GRAPHICS ADAPTER, PCI/SHORT/32BIT/5V, WEITEK P9100
  - 2708 Eicon ISDN DIVA PRO 2.0 PCI S/T Adapter
  - 2837 MVP MULTI-MONITOR ADAPTER, PCI/LONG/32BIT/3.3 OR 5V
  - 2854 3D (GXT500P), PCI/LONG/32BIT/3.3 OR 5V, GRAPHICS ADAPTER
  - 2855 3DX (GXT550P), PCI/LONG/32BIT/3.3 OR 5V, GRAPHICS ADAPTER
  - 2856 PCI/SHORT/32BIT/3.3 OR 5V, 7250 ATTACH ADAPTER
  - 8242 10/100BASET ETHERNET PCI/SHORT/32BIT/5V
- ISA adapters:
  - 2647 VIDEO CAPTURE ENHANCEMENT, ISA/SHORT
  - 2701 4 PORT SDLC, ISA/LONG, EIA 232/V.35/X.21
  - 2931 8-PORT, ISA/LONG, EIA232 ADAPTER/FAN-OUT BOX
  - 2932 8-PORT, ISA/LONG, EIA232/422 ADAPTER/FAN-OUT BOX
  - 2933 128-PORT, ISA/LONG, EIA232 ASYNCH CONTROLLER
  - 2961 1 PORT X.25, SDLC, PPP, ISA/LONG, ADAPTER (C1X)
  - 2971 TOKEN RING ADAPTER, ISA
  - 2981 ETHERNET ADAPTER, ISA, RJ45/BNC
  - 8240 A/M 3COM ETHERNET ISA/SHORT TP ONLY
  - 8241 A/M 3COM ETHERNET ISA/SHORT BNC/AUI
- Non-CHRP Graphics Adapters:
  - Gt3/Gt3i
  - Gt4/Gt4e/Gt4i/Gt4x/Gt4xi
  - GXT110P
  - GXT150L/GXT150M/GXT150P
  - GXT155L
  - GXT500
  - GXT500D
  - GXT500P
  - GXT550P (FC 2855 only)
  - GXT800M

- GXT1000™
- MVP MULTIPCI Adapter
- S15
- VIDEO OUTPUT OPTION (#3200) (FC 7254)
- 7250 ATTACH Adapter (FC 2856)

---

## **AIX 5L Version 5.2 Unsupported Functions and Filesets**

The following functions and filesets are not supported:

- 7318 Model P10/S20 Serial Communications Network Server
- AIX Xstation Manager®
- AIX Version 3.2 Network Installation Tools
- Remote Customer Support and Services
- SOMobjects® Base Toolkit
- Information Presentation Facility Runtime
- X11.vsm.helps
- X11.vsm.icons
- X11.vsm.rte
- GL 3.2
- power management
- IBM-850 locales
- libipfx.a
- devices.pci.b7105090
- The 7318 Serial Communications Network Server
- Network Terminal Accelerator
- The 9333 Serial Link DASD Subsystem
- CPU Gard
- devices.pci.331101e0

---

## Appendix B. Notices

This information was developed for products and services offered in the U.S.A.

IBM may not offer the products, services, or features discussed in this document in other countries. Consult your local IBM representative for information on the products and services currently available in your area. Any reference to an IBM product, program, or service is not intended to state or imply that only that IBM product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any IBM intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any non-IBM product, program, or service.

IBM may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing, to:

IBM Director of Licensing  
IBM Corporation  
North Castle Drive  
Armonk, NY 10504-1785  
U.S.A.

**The following paragraph does not apply to the United Kingdom or any other country where such provisions are inconsistent with local law:** INTERNATIONAL BUSINESS MACHINES CORPORATION PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some states do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement may not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. IBM may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

Licensees of this program who wish to have information about it for the purpose of enabling: (i) the exchange of information between independently created programs and other programs (including this one) and (ii) the mutual use of the information which has been exchanged, should contact:

IBM Corporation  
Dept. LRAS/Bldg. 003  
11400 Burnet Road  
Austin, TX 78758-3498  
U.S.A.

Such information may be available, subject to appropriate terms and conditions, including in some cases, payment of a fee.

The licensed program described in this document and all licensed material available for it are provided by IBM under terms of the IBM Customer Agreement, IBM International Program License Agreement or any equivalent agreement between us.

For license inquiries regarding double-byte (DBCS) information, contact the IBM Intellectual Property Department in your country or send inquiries, in writing, to:

IBM World Trade Asia Corporation  
Licensing  
2-31 Roppongi 3-chome, Minato-ku  
Tokyo 106, Japan

IBM may use or distribute any of the information you supply in any way it believes appropriate without incurring any obligation to you.

Information concerning non-IBM products was obtained from the suppliers of those products, their published announcements or other publicly available sources. IBM has not tested those products and cannot confirm the accuracy of performance, compatibility or any other claims related to non-IBM products. Questions on the capabilities of non-IBM products should be addressed to the suppliers of those products.

Any references in this information to non-IBM Web sites are provided for convenience only and do not in any manner serve as an endorsement of those Web sites. The materials at those Web sites are not part of the materials for this IBM product and use of those Web sites is at your own risk.

This information contains examples of data and reports used in daily business operations. To illustrate them as completely as possible, the examples include the names of individuals, companies, brands, and products. All of these names are fictitious and any similarity to the names and addresses used by an actual business enterprise is entirely coincidental.

---

## Trademarks

The following terms are trademarks of International Business Machines Corporation in the United States, other countries, or both:

AIX  
AIX 5L  
AnyNet  
DB2  
developerWorks  
ESCON  
eServer  
GXT1000  
IBM  
Micro Channel  
POWER2  
POWER4  
POWER5  
PowerPC  
PowerPC Reference Platform  
pSeries  
Redbooks  
RETAIN  
RS/6000  
S/390  
SOMobjects  
SP  
TotalStorage  
TURBOWAYS



VisualAge  
Xstation Manager

Java and all Java-based trademarks and logos are trademarks or registered trademarks of Sun Microsystems, Inc. in the United States, other countries, or both.

UNIX is a registered trademark of The Open Group in the United States and other countries.

Linux is a trademark of Linus Torvalds in the United States, other countries, or both.

Other company, product, or service names may be the trademarks or service marks of others.







Part Number: 16R2255

Printed in U.S.A.

GI10-0739-07



(1P) P/N: 16R2255

